# Panasonic BUSINESS







# Professional DISPLAYS

Line-up Catalogue February 2018





Worldwide Olympic Partner



Worldwide Paralympic Partner





### Panasonic Professional Displays Lineup





#### Indoor



High Brightness
 24/7 Use Reliability
 System Expandability

OpenPort PLA AF1 Series	ATFORM® N 500.d/m Port <sup>®</sup>	10dels 55" TH-55AF1	<b>49"</b> TH-49AF1	<b>42''</b> TH-42AF1
LinkRay Comp SF1H Series	patible Mod	55″	49"	42"
SF2H Series	700 <sub>cd/m</sub>	TH-555F1H	TH-495F1H	TH-425F1H
Link	Ray <sub>™</sub>	TH-80SF2H	TH-70SF2H	
<b>LF80</b> Series	700 <sub>celar</sub>	55" TH-55LF80	<b>49''</b> TH-49LF80	<b>42''</b> TH-42LF80
SF2 Series	450 <sub>od/m</sub>	65" TH-655F2	<b>55"</b> TH-555F2	<b>49''</b> TH-495F2
		<b>43"</b> TH-435F2		
C24/7 US	Media Player	ISPZ* Series only	ow Portrait SL	. <b>DT 2.D</b> O Series anly





### **Panasonic Professional Displays Lineup**

#### Multi Touch



#### Powerful and Intuitive Whiteboard

- Infrared Multi-touch
- Excellent Durability and
- Additional Features
- Universal Wireless Support (BF1 Series Only)



#### Petersen Automotive Museum

### On trend displays at Petersen Museum

The Petersen Automotive Museum partnered with Panasonic because they needed a combination of high-quality projectors and high-quality screens, as well as strategic support to help them achieve their vision and maintain their exhibits. They installed a total of 47 Panasonic projectors and 15 professional displays.



Equipment installed

PT-DZ780, PT-DZ870, TH-55LF80, TH-70LF50, TH-80LF50, TH-98LQ70, PT-RZ670, TH-55SF1H

#### Contemplating the natural world Keele University at Keele University

Pure AV utilises Panasonic LCD displays to turn a traditional 48 seat IT lab at School of Pharmacy at Keele University into a modern 60 seat collaborative learning space





Equipment installed TH-49LF80

#### Interactive Signage



ShadowSense<sup>™</sup> Multi-touch Very robust and reliable touchscreens

- High visibility and responsiveness in bright environments
- Remotely manageable



LF80-

SST Series

**AF1-**

700 cd/m

500.4

55"

TH-55LF80-SST

55'

TH-55AF1-SST TH-49AF1-SST TH-42AF1-SST **~24**/7 🚟 Multi ( Touch

49"

TH-49LF80-SST

49'

42"

42"

\*DigitalLink LE80-SST only

TH-42LF80-SST

Outdoor



Durability Against Rain/Dust System Expandability



### 🕨 4K UHD Display



84"

Model no.	TH-98LQ70	TH-84LQ70	TH-98LQ70L	TH-84LQ70L	
Screen Size (Diagonal)/Aspect Ratio	98-inch (2476.9 mm)/16:9	84-inch (2134.6 mm)/16:9	98-inch (2476.9 mm)/16:9	84-inch (2134.6 mm)/16:9	
Panel Type	IPS Panel/D-LED	IPS Panel/E-LED	IPS Panel/D-LED	IPS Panel/E-LED	
Effective Display Area (W x H)	2159 x 1214 mm (85.0" x 47.8")	1860 x 1047 mm (73.3" x 41.3")	2159 x 1214 mm (85.0" x 47.8")	1860 x 1047 mm (73.3" x 41.3")	
Resolution (H x V)	3840 x 2160	3840 x 2160	3840 x 2160	3840 x 2160	
Brightness (Typ)	500 cd/m <sup>2</sup>	500 cd/m <sup>2</sup>	500 cd/m <sup>2</sup>	500 cd/m <sup>2</sup>	
Contrast Ratio	1300 :1	1400 : 1	1300 :1	1400 : 1	
Dynamic Contrast Ratio	500000 :1	500000 :1	500000 :1	500000 :1	
Response Time	8 ms (G to G)	12 ms (G to G)	8 ms (G to G)	12 ms (G to G)	
Viewing Angle (Horizontal/Vertical)	178° / 178°	178° / 178°	178° / 178°	178° / 178°	
Panel Surface Treatment	Anti-Glare (Haze 1 %)	Anti-Glare (Haze 10 %)	Anti-Glare (Haze 1 %)	Anti-Glare (Haze 10 %)	
HDMI In	HDMI TYPE A Connector x4, HDMI 1*1/HDMI 2*1 (Up to	4K@50/60Hz], HDMI 3*1/HDMI 4*2 (Up to 2K@50/60Hz)	HDMI TYPE A Connector x4, HDMI 1*1/HDMI 2*1 (Up to	4K@50/60Hz], HDMI 3*1/HDMI 4*2 (Up to 2K@50/60Hz)	
DisplayPort In		1 (DP1.2a)*2	DisplayPort x		
DVI-D In	DVI-D 2		DVI-D 24		
Audio In (L/R)	Stereo Mini Jack (M3) x		Stereo Mini Jack (M3) x 1		
PC In		in x 1 (Female)* <sup>3</sup>	Mini D-sub 15-pi		
Audio In (L/R)	Stereo Mini Jack (M3) x 1		Stereo Mini Jack (M3) x 1		
Audio Out	Stereo Mini Jack (M3) x 1		Stereo Mini Jack (M3) x 1		
Serial In	D-sub 9-pin x 1, RS-232C Compatible		D-sub 9-pin x 1, RS-232C Compatible		
LAN	RJ45 x 1 100BASE-TX, Compatible with PJLink™ (Shared with DIGITAL LINK)		RJ45 x 1 100BASE-TX. Compatible with PJLink™ [Shared with DIGITAL LINK]		
DIGITAL LINK	RJ45 x 1 (Shared with LAN)		RJ45 x 1 (Shared with LAN)		
Function Slot	SLOT NX x 2 (Vacant)		SLOT NX x 2 (Vacant)		
Power Requirements	220-240 V AC		220-240 V AC. 50 Hz/60 Hz		
Power Consumption	620 W	540 W	620 W	540 W	
Power Off Condition	0.3 W	0.3 W	0.3 W	0.3 W	
Stand-by Condition	0.5 W	0.5 W	0.5 W	0.5 W	
Dimensions (W x H x D)	2233 x 1288 x 122 mm (87.9" x 50.7" x 4.8")	1949 x 1141 x 99 mm (76.7" x 44.9" x 3.9")	2233 x 1288 x 113 mm [87.9" x 50.7" x 4.5"]	1949 x 1141 x 92 mm (76.7" x 44.9" x 3.7")	
Carton Size (W x H x D)	2406 x 1520 x 460 mm (94.8" x 59.9" x 18.2")	2156 x 1361 x 404 mm [84.9" x 53.6" x 15.9"]	2406 x 1520 x 460 mm (94.8" x 59.9" x 18.2")	2156 x 1361 x 404 mm (84.9" x 53.6" x 15.9")	
Weight	Approx. 136.0 kg (299.9 lbs.)	Approx. 108.0 kg (238.1 lbs.)	Approx. 105.0 kg (231.5 lbs.)	Approx. 84.0 kg (185.2 lbs.)	
Gross Weight	Approx. 161.0 kg (355.0 lbs.)	Approx. 130.0 kg (286.6 lbs.)	Approx. 130.0 kg [286.6 lbs.]	Approx. 106.0 kg (233.7 lbs.)	
Protective Glass	Yes	Yes			
Built-in Speaker	20W [10W + 10		20W [10W + 10	W] (10% THD)	
Orientation	Landscap		Landscap		
Tilting Angle		nd 5 degrees with portrait setting*4	10 degrees with landscape setting a		
Operating Environment		% to 80 % (Non condensation) / Altitude 0-2400 m (7874 ft)*5	Temperature: 0 °C to 40 °C (32 °F to 104 °F) / Humidity: 20 %		
Storage Environment	Temperature: -20 °C to 60 °C (-4 °F to 140 °F		Temperature: -20 °C to 60 °C (-4 °F to 140 °F)		
Operating Time*6	24 h		24 h		
Pedestal	TY-ST103PF9	TY-ST85P12	TY-ST103PF9	TY-ST85P12	
Wall-hanging Bracket	TY-WK103PV9	_	TY-WK103PV9	-	
Ceiling-hanging Bracket	TY-CE103PS10*7	TY-CE85PS12*7	TY-CE103PS10*7	TY-CE85PS12*7	
Mobile Stand		TY-ST85PB1		TY-ST85PB1	
3G-SDI Terminal Board			— TY-TBN03G *Require		
Digital Interface Box		e 2 boards for 4K/60p B100G	ET-YFI		
DIGITAL LINK Switcher	EI-TF FT-YF		ET-YF		
DIOTTAL LINK SWITCHEI	EI-TF	02000	E1-1F1	12000	

84"

0 °C to 35 °C (32 °F to 95 °F) When using the unit where it is 1400 m (4593 ft) and higher and below 2400 m (7874 ft) above sea level, make sure [High altitude mode] is set to [ON].

#### $\sim$ A wide range of professional 4K required applications

#### Public Information

LQ70 Series





98"



• Control Rooms







06


07

### **LQ70** Series

### 4K UHD Display

#### High Color Reproduction (3D-LUT & 6-Axis Color Correction)

The color space on LCD displays tends to narrow when the luminance level drops, and it's often accompanied by color phase shifts. 3D-LUT (Look Up Table) Color Correction on the LQ70 Series has a look up table for each luminance level. Six Axis Coordinate Correction applies image processing to balance the six axes of the three primary colors (RGB) and their complementary colors (CMY). This keeps the intermediate shades of extremely fine colors vibrant and lifelike.





6-Axis (RGB/CMY) Color Correction

3-Axis (RGB) Color Correction

\* Images on screen are simulated.

#### Non-4K Sources Are Also Beautifully Compensated

Panasonic's new-generation image processing technology (Detail Clarity Processor3\*) also reproduces non-4K image content, such as Full-HD images and PC signals, with high picture quality. In addition, it compensates motion images for smooth, non-blurry display, which was difficult with conventional models. \* Optimizes the frequency and level of the input signal in horizontal and vertical directions to produce beautifully sharp, clear images.





Some large displays are blurry around the edges.

New-generation image

nrocessing technology

A sharp, clear image with crisp edges

#### Designed with Rugged Durability for Professional Use

The LQ70 Series has protective glass with 3.5J\* impact resistance on the front of the display. With its strong resistance to external impacts, this rugged design allows safe installation in places where many people walk by, such as train stations, airports, and shopping malls. The special frame construction also resists twisting to boost reliability during installation. Ideal for rental applications, where the panel is frequently transported and installed.

\* This value is from a Panasonic test. It does not imply a guaranteed value.



\* Except TH-98/84LQ70L.

Protective glass resists impacts Special latticed frame resists twisting

\* Images on screen are simulated.

#### **Portrait Installation** Capability

When the LQ70 Series is installed vertically, it can display a person in almost life-size dimensions. It is ideal for digital signage use because it faithfully reproduces the textures and colors of a model's clothing and accessories. It helps to maintain a high-quality brand image. Vertical installation also has no effect on the lifetime of the panel.



#### Capable of 4-Input Multi Display with No Processor Required

The LQ70 Series features a 4-Input Multi Display function. The image can be switched from a full-screen display to a 4-Input Multi Display with a single press of a remote control button. Ideal for checking details in various applications, such as videoconferences, digital signage, and surveillance monitoring.



\* Some restrictions exist for input signals and display splitting. \* 3G-SDI input and 4K image are not supported by the 4-Input Multi Display function.

#### **Designed for Easy Transportation** and Installation

By mounting eyebolts to the installation holes of the LQ70 Series and attaching hooks to the evebolts, the unit can be easily moved and installed using a hoisting device such as a crane. The tough frame resists twisting and distortion, thus reducing the burden on the installation staff.

\* The unit must be installed or uninstalled only by a specially trained installer.



#### **SLOT NX Versatile 4K Input**

The new SLOT NX makes it possible to change the interface to match the application. If the optional 3G-SDI Terminal Board is mounted, the LQ70 Series can be connected with SDI. This feature is convenient for use in broadcasting stations, for rental use and for long-distance connection. The LQ70 Series is expandable and will accommodate 4K input in the future.



\* All images shown are simulated. \* SLOT NX is not compatible with SLOT 2.0. \* Require 2 boards for 4K / 60p

#### **Indoor**

### AF1 Series









Model no.	TH-55AF1	TH-49AF1	TH-42AF1
Screen Size (Diagonal)/Aspect Ratio	55-inch (1387 mm)/16:9	49-inch (1232 mm)/16:9	42-inch (1064 mm)/16:9
Panel Type	IPS Panel/E-LED	IPS Panel/E-LED	IPS Panel/E-LED
Effective Display Area (W x H)	1209 x 680 mm (47.6" x 26.7")	1073 x 604 mm (42.2" x 23.7")	927 x 521 mm (36.5" x 20.5")
Resolution (H x V)	1920 x 1080	1920 x 1080	1920 x 1080
Brightness (Typ)	500 cd/m <sup>2</sup>	500 cd/m <sup>2</sup>	500 cd/m <sup>2</sup>
Contrast Ratio	1300:1	1300:1	1300:1
Dynamic Contrast Ratio	50000:1	50000:1	50000:1
Response Time	8 ms (G to G)	8 ms (G to G)	8 ms (G to G)
Viewing Angle (Horizontal/Vertical)	178°/178° (CR≥10)	178°/178° (CR≥10)	178°/178° (CR≥10)
Panel Surface Treatment	Anti-Glare (Haze 10 %)	Anti-Glare (Haze 10 %)	Anti-Glare (Haze 10 %)
OS		id 4.4.3	Android 4.4.3
CPU			
		.0 GHz (Quad)	Cortex-A9, 1.0 GHz (Quad)
Memory		/ ROM 8 GB	RAM 1 GB / ROM 8 GB
VIDEO In	BNC x 1 (Shared v	vith Component In)	BNC x 1 (Shared with Component In)
Audio In (L/R)	Stereo Mini Jack (M3) x 1 (	Shared with Component In)	Stereo Mini Jack (M3) x 1 (Shared with Component In)
HDMI In	HDMI Type A	Connector x 2	HDMI Type A Connector x 2
Component/RGB In	BNC x 1 set (Sha	red with VIDEO In)	BNC x 1 set (Shared with VIDEO In)
Audio In (L/R)		1 (Shared with Video In)	Stereo Mini Jack (M3) x 1 (Shared with Video In)
DVI-D In		4-pin x 1	DVI-D 24-pin x 1
Audio In (L/R)		x 1 (Shared with PC In)	Stereo Mini Jack (M3) x 1 (Shared with PC In)
DVI-D Out		4-pin x 1	DVI-D 24-pin x 1
PC In			
		pin x1 (Female)	Mini D-Sub 15-pin x1 (Female)
Audio In (L/R)		1 (Shared with DVI-D In)	Stereo Mini Jack (M3) x 1 (Shared with DVI-D In)
Audio Out (L/R)		Jack (M3) x 1	Stereo Mini Jack (M3) x 1
Serial In/Out		RS-232C Compatible	D-sub 9-pin x 1/x 1, RS-232C Compatible
USB	USB connector (TYPE A) x 1, DC	5 V/1 A (USB3.0 is not supported)	USB connector (TYPE A) x 1, DC 5 V/1 A (USB3.0 is not suppo
IR In/Out	Stereo Mini Ja	ck (M3) x 1 / x 1	Stereo Mini Jack (M3) x 1 / x 1
LAN	RJ45 x 1 for Network Connection, 10BASE-T/100	BASE-TX/1000BASE-T, Compatible with PJLink™	RJ45 x 1 for Network Connection, 10BASE-T/100BASE-TX/1000BASE-T, Compatible with F
USB	USB2.0 connector (TYF	PE A) x 3, DC 5 V/500 mA	USB2.0 connector (TYPE A) x 3, DC 5 V/500 mA
Micro-USB	Micro USB (	Connector x 1	Micro USB Connector x 1
microSD card slot	microSD m	icroSDHC x 1	microSD, microSDHC x 1
Wireless LAN		.11a/b/q/n	IEEE 802.11a/b/g/n
Power Requirements	220-240 V AC. 50 Hz/60 Hz	220-240 V AC. 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz
Power Consumption	190 W	175 W	155 W
Power Off Condition			
	Approx. 0.3 W	Approx. 0.3 W	Approx. 0.3 W
Stand-by Condition	Approx. 20 W (When [OpenPort P	PLATFORM standby] is set to [Off]) LATFORM standby] is set to [On]]	Approx. 0.5 W (When [OpenPort PLATFORM standby] is set to Approx. 20 W (When [OpenPort PLATFORM standby] is set to
Dimensions (W x H x D)	1229 x 699 x 72 *mm (48.4" x 27.6" x 2.8" *)	1093 x 623 x 72 *mm (43.1" x 24.6" x 2.8" *	947 x 541 x 72 *mm (37.3" x 21.3" x 2.8" *)
Carton Size (W x H x D)	1444 x 922 x 223 mm (56.9" x 36.3" x 8.8")	1308 x 846 x 203 mm (51.5" x 33.4" x 8.0")	1123 x 743 x 203 mm (44.3" x 29.3" x 8.0")
Bezel Width	6.3 mm (0.25")	6.3 mm (0.25")	6.3 mm (0.25")
Weight	Approx. 25.0 kg (55.2 lbs.)	Approx. 19.3 kg (42.6 lbs.)	Approx. 15.6 kg (34.4 lbs.)
Gross Weight	Approx. 33.0 kg (72.8 lbs.)	Approx. 26.0 kg (57.4 lbs.)	Approx. 21.0 kg (46.3 lbs.)
Pitch for Wall-Hanging	VESA Compliant 400x 400 mm (15.8" x 15.8")	VESA Compliant 400x 400 mm (15.8" x 15.8")	VESA Compliant 200 x 200 mm (7.9" x 7.9")
Built-in Speakers	20 W [10 W + 10 W]	20 W [10 W + 10 W]	20 W [10 W + 10 W]
Orientation		nt 0-45 degrees for both left and right)	Landscape/Portrait (Angle adjustment 0-45 degrees for both left an
Tilting Angle* <sup>1</sup>		with landscape/portrait setting*1 forward/backward tilting installation.]	0-45 degrees forward/backward with landscape/portrait settin (Angle adjustment is not possible for forward/backward tilting instal
Operating Environment		4 °F)*2 : 0 °C to 35 °C (32 °F to 95 °F)*3 / % (Non-condensation)	Temperature: 0 °C to 40 °C [32 °F to 104 °F]*2 : 0 °C to 35 °C [32 °F to 95 Humidity: 20 % to 80 % [Non-condensation]
Storage Environment	-	) / Humidity: 20 % to 80 % (Non Condensation)	Temperature: -20 °C to 60 °C [-4 °F to 140 °F] / Humidity: 20 % to 80 % [Non Conder
Operating Time*4		/day	24 h/day
Pedestal	TY-ST43PE8	TY-ST43PE8	TY-ST43PE8
Early Warning Software*5	ET-SWA100 Series	ET-SWA100 Series	ET-SWA100 Series
Auto Display Adjustment Upgrade Kit*6 Multi Window Processor*7	TY-VUK10 ET-MWP100G	TY-VUK10 ET-MWP100G	TY-VUK10 ET-MWP100G

\*1: Please contact your sales representative with regard to the tilt angle before installation. \*2: for up to 1400 m (4593 ft) altitude \*3: for between 1400 m (4593 ft) and 2800 m (9186 ft) altitude. Depending on the temperature or humidity conditions, uneven brightness may be observed. This is not a malfunction. This unevenness will disappear while applying current continuously. If not, consult the distributor. \*4: In case of long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain on the screen. However, image retention can gradually disappear by displaying a moving images. \*5: Suffix of the part number may differ depending on the license type. \*6: Download the latest Video Wall Manager from PASS in advance. [https://panasonic.net/cns/prodisplas/pass/] \*7: The availability varies depending on the country.

Feature video



AF1 Series: Pro Signage Display Featuring Android -based OpenPort PLATFORM



To know more visit: https://business.panasonic.co.uk/ visual-system/openport-platform

★ The handle part excluded, the thickness is 57 mm (2.3").

### **AF1** Series

#### Evolving with Your Needs

Android<sup>™</sup>- and HTML5-based OpenPort PLATFORM<sup>®</sup> Gives Freedom to Customize and Grow with Digital Signage Apps, Simplifies Everyday Use. The AF1 Series incorporates a high-performance SoC (System on a Chip) with a 1 GHz Quad-Core CPU, 1 GB RAM, 8 GB Storage. All this is supported by an alliance with a leading signage software developer to jointly verify application operation. To find more information visit our website: http://business.panasonic.co.uk/ visual-system/openport-platform


### нтм 5

The Android robot is reproduced or modified from work created and shared by Google and used according to terms described in the Creative Commons 3.0 Attribution License.

OpenPort

#### Evolving with Your Needs


Simple, expandable, and reliable. the AF1 Series' Android™-based OpenPort PLATFORM® is powered by a high-performance SoC (System on a Chip) with a 1 GHz quad-core CPU, 1 GB of memory, and 8 GB\* of internal storage. Together with verified apps created by global alliance partners for custom signage and other roles in business, these adaptive displays deliver your message with maximum impact now and in the future.



\* Total capacity of storage including OS

#### No Need for External Devices and Cables

Thanks to the built-in media player function, external devices such as set-top boxes, PCs, and associated cabling are not required for digital signage applications. Wireless functionality paves the way to simple, stress-free installation while saving you time and money.



#### Panasonic Original Home Screen

*F*\_

+

\*

**\***\*

STATUS

Initial setup of network and language preferences is easy using the remote controller\* and original Panasonic Home Screen.



#### Simple App Installation

Applications are easily accessed and installed via Panasonic App Server\*, which streamlines settings before operation. App installation is also enabled via USB drive or microSD card. \* Certain partner apps not supported

Panasonic Ann Server F1 Series

USB and microSD can

#### **Panasonic API Expands Application Functions**

Panasonic's clear and intuitive API (Application Programming Interface) enables the expansion of application functions, allowing the display to be controlled remotely without need of RS232C or other complicated applications.



#### A Reliable, Fully Certified Platform

The OpenPort PLATFORM<sup>®</sup> based on Android<sup>™</sup> is fully certified by Google to assure stable, secure, and reliable operation.

#### Mutual Check with App Alliance Partners

Applications running on OpenPort PLATFORM® are thoroughly checked by alliance partners and Panasonic for stable and secure operation

See our partners: http://business.panasonic.co.uk/visual-system/ openport-platform/partners

#### **Optional Early Warning Software** (ET-SWA100 Series)

Optional ET-SWA100 Series\* Early Warning Software monitors the displays and projectors connected to an intranet and informs you when an abnormality is detected or there are symptoms of trouble. With this software installed, a monitoring server can be controlled remotely via tablet or PC.

\* Part number suffix may differ depending on the license type.

#### Make Your Signage Easy with Panasonic Application

AF1 Series displays include a builtin Signage Player Application\* that eliminates need of an external Settop Box (STB). As well as saving space, your signage system becomes smart and simple. \* OpenPort PLATFORM® Version 2.0 firmware (or later) is required.

#### Play Content Automatically with Scheduling Function


Content Management Software for PC Version 1.1 (free) enables easy playlist creation with media support including combinations of still and video images. You can set up schedules for playing and closing your media playlist at predetermined dates and times.

#### Start 9:00 AM 12:00 PM 7:00 PM Fnd Plavlist 3 ☀ Plavlist Plavlist 2 Video Video + Still Still

#### Bright and Stylish IPS Display


🚺 Indoor

The slim-bezel AF1 Series is offered in 42-, 49-, and 55-inch sizes and features an edge-lit LED IPS panel with a high 500 cd/m<sup>2</sup> of brightness. This efficient technology assures uncommonly good off-axis visibility, preserving accurate color reproduction even in bright ambient light. Furthermore, the AF1 Series features a slim 6.3 mm-bezel-width that boosts perceived image size while enhancing any interior design.



#### **Supports Connection of Peripheral Devices**

Peripheral devices such as a mouse, keyboard, or USB camera can be connected to AF1 Series displays to further expand functionality.



#### Supports External Memory Devices

USB drives and microSD cards can also be used to expand the 8 GB internal memory storage capacity.



For more information about Content Management Software Version 1.1. please visit

https://panasonic.net/cns/prodisplays/download/software/

#### Convenient Playlist and Schedule Syncing

Plavlists and schedules created with Content Management Software can be transferred to displays with USB memory, microSD Card, or via LAN. Synchronized playback on multiple displays is also supported.



SF2H/SF1H Series	NEW 80"	NEW 70''	55"	
Model no.	TH-80SF2H	TH-70SF2H	TH-55SF1H	TH-498
Screen Size (Diagonal)/Aspect Ratio	80-inch (2032 mm)/16:9	70-inch (1765 mm)/16:9	55-inch (1387 mm)/16:9	49-inch (1232
_ Panel Type	VA Panel/E-LED	VA Panel/E-LED	IPS Panel/E-LED	IPS Panel/
Effective Display Area (W x H)	1771 x 996 mm (69 7" x 39 2")	1538 x 865 mm (60 5" x 34 0")	1209 x 680 mm (47 6" x 26 7")	1073 x 604 mm (

Model no.	111-0001 211	111-7001 211	111-5561 111	111-4301 111	111-4201 111		
Screen Size (Diagonal)/Aspect Ratio	80-inch (2032 mm)/16:9	70-inch (1765 mm)/16:9	55-inch (1387 mm)/16:9	49-inch (1232 mm)/16:9	42-inch (1064 mm)/16:9		
Panel Type	VA Panel/E-LED	VA Panel/E-LED	IPS Panel/E-LED	IPS Panel/E-LED	IPS Panel/E-LED		
Effective Display Area (W x H)	1771 x 996 mm (69.7" x 39.2")	1538 x 865 mm (60.5" x 34.0")	1209 x 680 mm (47.6" x 26.7")	1073 x 604 mm (42.2" x 23.7")	927 x 521 mm (36.5" x 20.5")		
Resolution (H x V)	1920 x 1080	1920 x 1080	1920 x 1080	1920 x 1080	1920 x 1080		
Brightness (Typ) +	700 cd/m <sup>2</sup>	700 cd/m <sup>2</sup>	700 cd/m <sup>2</sup>	700 cd/m <sup>2</sup>	700 cd/m <sup>2</sup>		
Contrast Ratio	5000:1	5000:1	1300:1	1300:1	1300:1		
Dynamic Contrast Ratio	50000:1	50000:1	50000:1	50000:1	50000:1		
Response Time	4.0 ms (G to G)	8.0 ms (G to G)	8 ms (G to G)	8 ms (G to G)	8 ms (G to G)		
Viewing Angle (Horizontal/Vertical)	176°/176° (CR≥10)	176°/176° (CR≥10)	178°/178° (CR≥10)	178°/178° (CR≥10)	178°/178° (CR≥10)		
Panel Surface Treatment	Anti-Glare (Haze 5 %)	Anti-Glare (Haze 12 %)	Anti-Glare (Haze 10 %)	Anti-Glare (Haze 10 %)	Anti-Glare (Haze 10 %)		
VIDEO In				BNC x 1 (Shared with Component /RGB Y/G)			
Audio In (L/R)	4-pole Mini Jack (M3) x 1 (Audio In s	shared with DVI-D In/PC In/Video In)	S	tereo Mini Jack (M3) x 1 (Shared with Component	In)		
HDMI In	HDMI Type A	Connector x 2		HDMI Type A Connector x 2			
Component/RGB In	принтурелт			BNC x 1 set (Shared with Video In)			
Audio In (L/R)				Stereo Mini Jack (M3) x 1 (Shared with Video In)			
DVI-D In	DVI-D 24-pin x 1 (DVI Revision 1.0	- compliant) HDCR 1.1 compatible		DVI-D 24-pin x 1			
Audio In (L/R)	4-pole Mini Jack (M3) x 1			Stereo Mini Jack (M3) x 1 (Shared with PC In)			
DVI-D Out	4-pole Mini Jack (M3) x 1 DVI-D 24-pin x 1 (DVI Revision 1.0			DVI-D 24-pin x 1			
PC In	Mini D-sub 15-pin x 1			Mini D-Sub 15-pin x 1 (Female)			
Audio In (L/R)	4-pole Mini Jack (M3) x 1 (S			Stereo Mini Jack (M3) x 1 (Shared with DVI-D In)			
Audio III (L/R) Audio Out (L/R)							
Serial In/Out	Stereo Mini J	N 7		Stereo Mini Jack (M3) x 1			
	D-sub 9-pin x 1/x 1,		DUC 4	D-sub 9-pin x 1/x 1, RS-232C Compatible	11. I AND		
DIGITAL LINK		le with PJLink™ (Shared with LAN)		RJ45 x 1 100BASE-TX, Compatible with PJLink™ (Shared with LAN)			
LAN	RJ45 x 1, 100BASE-TX, Compatible wit	· · · · · · · · · · · · · · · · · · ·	RJ45 X 1 100	RJ45 x 1 100BASE-TX, Compatible with PJLink™ (Shared with DIGITAL LINK)			
IR In/Out	Stereo Mini Jac			Stereo Mini Jack (M3) x 1 / x 1			
USB	USB Type A Connector x 1, DC 5			USB Type A Connector x 1, DC 5V/1A (USB 3.0 is not supported.)			
Power Requirements	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz		
Power Consumption	380 W	235 W	190 W	175 W	155 W		
Power Off Condition	Approx. 0.3 W	Approx. 0.3 W	Approx. 0.3 W	Approx. 0.3 W	Approx. 0.3 W		
Stand-by Condition	Approx. 0.5 W	Approx. 0.5 W	Approx. 0.5 W	Approx 0.5 W	Approx 0.5 W		
Dimensions (W x H x D)	1835 x 1060 x 82 mm (72.3" x 41.8" x 3.3")	1580 x 919 x 80 mm (62.2" x 36.2" x 3.2")	1229 x 699 x 72*mm (48.4" x 27.6" x 2.8"*)	1093 x 623 x 72*mm (43.1" x 24.6" x 2.8"*)	947 x 541 x 72*mm (37.3" x 21.3" x 2.8"*		
Carton Size (W x H x D)	1970 x 1191 x 351 mm (77.6" x 46.9" x 13.9")	1715 x 1050 x 351 mm (67.6" x 41.4" x 13.9")	1444 x 922 x 223 mm (56.9" x 36.3" x 8.8")	1308 x 846 x 203 mm (51.5" x 33.4" x 8.0")	1123 x 743 x 203 mm (44.3" x 29.3" x 8.0"		
Bezel Width	R/L/T/B: 28.5 mm (1.12")	R/L: 18.6 mm (0.73"), T/B: 23.6 mm (0.92")	R/L/T/B: 6.3 mm (0.25")	R/L/T/B: 6.3 mm (0.25")	R/L/T/B: 6.3 mm (0.25")		
Weight	Approx. 62.0 kg (135.0 lbs.)	Approx. 45.0 kg (99.0 lbs.)	Approx. 24.9 kg (54.9 lbs.)	Approx. 19.2 kg (42.4 lbs.)	Approx. 15.5 kg (34.2 lbs.)		
Gross Weight	Approx. 73.0 kg (159.0 lbs.)	Approx. 55.0 kg (119.0 lbs.)	Approx. 33.0 kg (72.8 lbs.)	Approx. 26.0 kg (57.4 lbs.)	Approx. 20.0 kg (44.1 lbs.)		
Pitch for Wall-Hanging	VESA compliant 600 x 400 mm (23.6" x 15.8")	VESA compliant 400 x 400 mm (15.8" x 15.8")	VESA Compliant 400 x 400 mm (15.8" x 15.8")	VESA Compliant 400 x 400 mm (15.8" x 15.8")	VESA compliant 200 x 200 mm (7.9" x 7.9"		
Built-in Speakers	20 W [10 W + 10 W]	20 W [10 W + 10 W]	20 W [10 W + 10 W]	20 W [10 W + 10 W]	20 W [10 W + 10 W]		
Orientation	Landscape/Portrait (Angle adjustment 0-45 degree	ees for both left and right: landscape setting only)	Landscape/	Portrait (Angle adjustment 0-45 degrees for both I	eft and right)		
Tilting Angle	0-20 degrees forward/backward (Angle adjustment is not possible for			0-45 degrees forward/backward with landscape/portrait setting*1 (Angle adjustment is not possible for forward/backward tilting installation.)			
Operating Environment	Temperature: 0 °C to 40 °C (32 °F to 104 °F)*2 : 0 °C to 35 °C (32 °F to 95 °F)*3 / Humidity: 20 % to 80 % (Non-condensation)		Temperature: 0	Temperature: 0 °C to 40 °C (32 °F to 104 °F)* <sup>2</sup> : 0 °C to 35 °C (32 °F to 95 °F)* <sup>3</sup> / Humidity: 20 % to 80 % (Non-condensation)			
Storage Environment	Temperature: -20 °C to 60 °C (-4 °F to 140 °F )	/ Humidity: 20 % to 80 % ( Non-condensation)	Temperature: -20 °C	to 60 °C (-4 °F to 140 °F) / Humidity: 20 % to 80 °	% (Non-condensation)		
Operating Time*4	24 h			24 h/day			
Pedestal	TY-ST75PE9	TY-ST75PE9	TY-ST43PE8	TY-ST43PE8	TY-ST43PE8		
Digital Interface Box	ET-YFB100G	ET-YFB100G	ET-YFB100G	ET-YFB100G	ET-YFB100G		
DIGITAL LINK Switcher	ET-YFB200G	ET-YFB200G	ET-YFB200G	ET-YFB200G	ET-YFB200G		
Early Warning Software*5	ET-SWA100 Series	ET-SWA100 Series	ET-SWA100 Series	ET-SWA100 Series	ET-SWA100 Series		
Auto Display Adjustment Upgrade Kit*6	TY-VUK10	TY-VUK10	TY-VUK10	TY-VUK10	TY-VUK10		
1 7 7 10							
Multi Window Processor*7 ease contact your sales representative with reg	ET-MWP100G gard to the tilt angle before installation.*2: for up to 140	ET-MWP100G D m (4593 ft) altitude	ET-MWP100G + The brightness of the display panel is equivalent t	ET-MWP100G to about 75% its full capacity, when the Light ID is tran	ET-MWP100G smitted. The displayed image may flicke		

\*3: for between 1400 m (4593 ft) and 2800 m (9186 ft) altitude

\*4: In case of long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain on the screen. However, image retention can gradually disappear by displaying a moving images. \*5: Multi Monitoring & Control Software Ver2.0 or later is required. Suffix of the part number may differ depending on the license type.

\*6: Download the latest Video Wall Manager from Global Website in advance. (https://panasonic.net/cns/prodisplays/download/software/vwm/)

\*7: The availability varies depending on the country.

OPTION

14

DISPLAY PANEI

+ The brightness of the display panel is equivalent to about 75% its full capacity, when the Light ID is transmitted. The displayed image may flicker. but this is due to a change in the brightness during Light ID transmission and not due to trouble.

Standard

SF1H

1.9

TH-42SF1H

 $\bigstar$  The handle part excluded, the thickness is 57 mm (2.3").

Depending on the temperature or humidity conditions, uneven brightness may be observed. This is not a malfunction. This unevenness will disappear while applying current continuously. If not, consult the distributor

### **SF2H/SF1H** Series



Light ID: 010101..

000000

SF1H Series

#### Built-in Light ID Transmission Function Sends and Receives Information

Panasonic has developed the most advanced mobile content delivery service to date, using visible light communication. LinkRay enables ordinary smartphones to read IDs in light sent from LED transmitters, such as displays (SF1H and SF2H Series) or LED lighting, and connect to associated web content. End users connect to content quickly, easily and securely through a simple, fast, intuitive and impactful end user experience.







Works Even in Crowds Receives as long as the light reaches the smartphone.

#### **Usage Case Examples & Benefits**

Receives the signal within 0.3 seconds











-Digital Signage Coupon Delivery

#### Retail / Foodservices / Advertising

Follow-up your call to action on customer devices, provide buying incentives that convert to sales, enable online ordering, and expand customer relationship management and insight.

#### Airports / Transit / City Services

Provide scheduling, access assistance, city information, and translation services to individuals, track their movements, and enable "smart city" capabilities.

#### Museums / Exhibitions / Showrooms

Provide creative content beyond the physical limits of exhibits, track and understand the visitor experience, and stay engaged. Send multilingual info and display it on a smartphone.

#### Applications for LinkRay

Panasonic provides a dedicated LinkRay Solution app for iOS/Android<sup>™</sup>. Users can download to supported smartphones and tablets free.



Supported Operating Systems



Note: Some devices may not operate correctly even if minimum requirements are met. To get the latest information concerning devices tested for compatibility, please visit the Panasonic LinkRay website. https://panasonic.net/cns/LinkRay/

#### LinkRay Cloud Platform

Web Links associated to each ID can be easily managed on the LinkRay Cloud Platform or a Content Management System at any time.





LinkRay [Introducing the Technology]





LinkRay [Use Cases]



LinkRay Solution@Live & Event Industrial Exhibition

#### LinkRay(TM) ID modulator for use with signboards or LED light sources

In addition to our range of Professional Displays equipped with built-in LinkRay™ technology, Panasonic provides a flexible solution to make LED lighting capable of transmitting LinkRay IDs.

Panasonic is offering three types of modulators.

The variable ID modulator AL-A001GL can handle an unlimited number of ID signals, allowing the scheduling and management of variable content. It is compatible with a 12-24V LED light source up to 50W, with daisy chaining also possible. This is the best option to equip larger signboards with LinkRay, for example, and for integration with variable content management system.

The fixed ID modulator NOTN70101 is designed for large LED signboards and showcase installations, and sends one ID signal. The small fixed ID modulator XC-ALS01W-1 is compact and lightweight, powered over USB up to 7W. It is especially suitable for low-cost and space-limited installations, such as product showcases, or low-power lighting, such as table-top ordering applications.



AL-A001GL LinkRay variable ID modulator 50W: 12-24V Dimensions: 148x43x33mm; 200g Ideal for large LED sign panels from A3 to A0 sizes with variable contents

NOTN70101 LinkRay fixed ID modulator 60W: 12-24V Dimensions: 182x40x22.5mm; 175g Ideal for large LED sign panels from A3 to A0 sizes







16

### LF80 Series

# 55"

49"



42"

			42
Model no.	TH-55LF80	TH-49LF80	TH-42LF80
Screen Size (Diagonal)/Aspect Ratio	55-inch (1387 mm)/16:9	48-inch (1232 mm)/16:9	42-inch (1064 mm)/16:9
Panel Type	IPS Panel/E-LED	IPS Panel/E-LED	IPS Panel/E-LED
Effective Display Area (W x H)	1209 x 680 mm (47.6" x 26.7")	1073 x 604 mm (42.2" x 23.7")	927 x 521 mm (36.5" x 20.5")
Resolution (H x V)	1920 x 1080	1920 x 1080	1920 x 1080
Brightness (Typ)	700 cd/m <sup>2</sup>	700 cd/m <sup>2</sup>	700 cd/m <sup>2</sup>
Contrast Ratio	1300:1	1300:1	1300:1
Dynamic Contrast Ratio	50000:1	50000:1	50000:1
Response Time	8 ms (G to G)	8 ms (G to G)	8 ms (G to G)
Viewing Angle (Horizontal/Vertical)	178°/178° (CR≥10)	178°/178° (CR≥10)	178°/178° (CR≥10)
Panel Surface Treatment	Anti-Glare (Haze 10 %)	Anti-Glare (Haze 10 %)	Anti-Glare (Haze 10 %)
VIDEO In		Component /RGB Y/G)	BNC x 1 (Shared with Component /RGB Y/G)
Audio In (L/R)		Shared with Component In)	Stereo Mini Jack (M3) x 1 (Shared with Component In)
HDMIIn		Connector x 2	HDMI Type A Connector x 2
Component/RGB In		red with Video In)	BNC x 1 set (Shared with Video In)
Audio In (L/R)		1 (Shared with Video In)	Stereo Mini Jack (M3) x 1 (Shared with Video In)
DVI-D In	DVI-D 2		DVI-D 24-pin x 1
Audio In (L/R)	Stereo Mini Jack (M3)		Stereo Mini Jack (M3) x 1 (Shared with PC In)
DVI-D Out	DVI-D 2		DVI-D 24-pin x 1
PC In	Mini D-Sub 15-		Mini D-Sub 15-pin x 1 (Female)
Audio In (L/R)		· · · · · · · · · · · · · · · · · · ·	Stereo Mini Jack (M3) x 1 (Shared with DV-D In)
Audio Out (L/R)	Stereo Mini Jack (M3) x 1 (Shared with DVI-D In) Stereo Mini Jack (M3) x 1		Stereo Mini Jack (M3) x 1
Serial In/Out			D-sub-9-pin x 1/x 1, RS-232C Compatible
DIGITAL LINK	D-sub 9-pin x 1/x 1, RS-232C Compatible RJ45 x 1 100BASE-TX, Compatible with PJLink™ (Shared with LAN)		RJ45 x 1 1008ASET X, Compatible with PJLink <sup>®</sup> (Shared with LAN)
LAN	RJ45 x 1 100BASE-TX, Compatible with PJLink (Shared with EAN)		R45 x1 100805CF n2 Compatible with PJLink" (Shared with DISTAL LINK)
IR In/Out	Stereo Mini Jack (M3) x 1 / x 1		Stereo Mini Jack (M3) x 1 / x 1
USB	USB Type A Connector x 1, DC 5V/1A (USB 3.0 is not supported.)		USB Type A Connector x 1, DC 5V/1A (USB 3.0 is not supported.)
Function Slot	USB Type A connector x 1, DC 3	W/TA (03b 5.0 is not supported.)	USB Type A connector x 1, DC 3v/1A (USB 5.0 is not supported.)
Power Requirements	220-240 V AC, 50 Hz/60 Hz		
Power Consumption	190 W	175 W	220-20 V AC, 30 1120 112
Power Off Condition	Approx. 0.3 W	Approx. 0.3 W	Approx. 0.3 W
Stand-by Condition	Approx. 0.5 W	Approx. 0.5 W	Approx. 0.5 W
Dimensions (W x H x D)	1229 x 699 x 72 <sup>*</sup> mm (48.4" x 27.6" x 2.8" )	1093 x t 23 x 72 * mm (43.1" x 24.6" x 2.8" )*	947 x 541 x 72 <sup>*</sup> mm (37.3" x 21.3" x 2.8" ) <sup>*</sup>
Carton Size (W x H x D)	1444 x 922 x 223 mm (56.9" x 36.3" x 8.8")	1308 x 846 x 203 mm (51.5" x 33.4" x 8.0")	94/243 × 203 mm (44.3" × 29.3" × 8.0")
Bezel Width	6.3 mm (0.25")	6.3 mm (0.25")	6.3 mm (0.25")
Weight	Approx. 24.7 kg (54.5 lbs.)	Approx. 19.0 kg (41.9 lbs.)	6.5 min (0.25 ) Approx. 15.3 kg (33.7 lbs.)
Gross Weight	Approx. 24.7 kg (54.5 lbs.) Approx. 32.0 kg (70.6 lbs.)	Approx. 19.0 kg (41.9 lbs.) Approx. 26.0 kg (57.4 lbs.)	Approx. 15.5 kg (55.7 lbs.) Approx. 20.0 kg (44.1 lbs.)
Pitch for Wall-Hanging			
Built-in Speakers	VESA Compliant 400 x 400 mm (15.8" x 15.8")	VESA Compliant 400 x 400 mm (15.8" x 15.8")	VESA compliant 200 x 200 mm (7.9* x 7.9*)
Orientation	20 W [10 W + 10 W]	20 W [10 W + 10 W]	20 W [10 W + 10 W]
			Landscape/Portrait (Angle adjustment 0-45 degrees for both left and right) 0-45 degrees forward/backward with landscape/portrait setting*1 (Angle adjustment is not possible for forward/backward tilting installation.)
Tilting Angle			
Operating Environment			Temperature: 0 °C to 40 °C (32°F to 104°F)*3 : 0 °C to 35 °C (32 °F to 95 °F)*4 / Humidity: 20 % to 80 % (Non-condensation)
Storage Environment			Temperature: -20 °C to 60 °C (-4 °F to 140 °F) / Humidity: 20 % to 80 % (Non-condensation)
Operating Time*5	T) ( (T (2005)	TY-ST43PE8	24 h/day
Pedestal	TY-ST43PE8	1Y-5143PE8	TY-ST43PE8
Wall-hanging Bracket	-	_	
Digital Interface Box	ET-YFB100G	ET-YFB100G	ET-YFB100G
DIGITAL LINK Switcher	ET-YFB200G	ET-YFB200G	ET-YFB200G
Digital Interface Box DIGITAL LINK Switcher Early Warning Software*6	ET-SWA100 Series	ET-SWA100 Series	ET-SWA100
Auto Display Adjustment Upgrade Kit*/	TY-VUK10	TY-VUK10	ΤΥ-٧υΚ10
Multi Window Processor*8	ET-MWP100G	ET-MWP100G	ET-MWP100G

\*1: Please contact your sales representative with regard to the tilt angle before installation.

\*2: If the temperature is 40 °C to 60 °C (104 °F to 140 °F), please keep in humidity 20 % to 40 %. \*3: for up to 1400 m (4593 ft) altitude

\*4: for between 1400 m (4593 ft) and 2800 m (9186 ft) altitude

Depending on the temperature or humidity conditions, uneven brightness may be observed. This is not a malfunction. This unevenness will disappear while applying current continuously. If not, consult the distributor.

\*5: In case of long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain

on the screen. However, image retention can gradually disappear by displaying a moving images.

\*6: Suffix of the part number may differ depending on the license type.

\*7: Download the latest Video Wall Manager from PASS in advance. (https://panasonic.net/cns/prodisplays/pass/)

\*8: The availability varies depending on the country.

 $\bigstar$  The handle part excluded, the thickness is 57 mm (2.3").

### SF2 Series

65"

	CO	55"	49"	43"
Model no.	TH-65SF2	TH-55SF2	TH-49SF2	TH-43SF2
Screen Size (Diagonal)/Aspect Ratio	65-inch (1639 mm)/16:9	55-inch (1387 mm)/16:9	49-inch (1232 mm)/16:9	43-inch (1079 mm)/16:9
Panel Type	IPS Panel/E-LED	IPS Panel/E-LED	IPS Panel/E-LED	IPS Panel/E-LED
Effective Display Area (W x H)	1428 x 803 mm (52.6" x 31.6")	1209 x 680 mm (47.6" x 26.7")	1073 x 604 mm (42.2" x 23.7")	941 x 529 mm (37.0" x 20.8")
lesolution (H x V)	1920 x 1080	1920 x 1080	1920 x 1080	1920 x 1080
rightness (Typ)	450 cd/m <sup>2</sup>	450 cd/m <sup>2</sup>	450 cd/m <sup>2</sup>	450 cd/m <sup>2</sup>
ontrast Ratio	1300:1	1100:1	1100:1	1100:1
ynamic Contrast Ratio	50000:1	50000:1	50000:1	50000:1
esponse Time	10 ms (G to G)	12 ms (G to G)	12 ms (G to G)	12 ms (G to G)
ewing Angle (Horizontal/Vertical)	178°/178°	178°/178° (CR≥10)	178°/178° (CR>10)	178°/178° (CR≥10)
nel Surface Treatment	Anti-Glare (Haze 1 %)	Anti-Glare (Haze 1 %)	Anti-Glare (Haze 1 %)	Anti-Glare (Haze 1 %)
DEO In/Audio In				
DEO IN/Addio IN	4-pole Mini-		4-pole Mini-j	
omponent/RGB In	HDMI Type A	connector x 2	HDMI Type A (	connector X Z
omponent/RGB In Jdio In (L/R)				-
	-	-	-	-
VI-D In	DVI-D 24-pin x 1 (DVI Revision 1.0		DVI-D 24-pin x 1 (DVI Revision 1.0	
udio In (L/R)	4-pole Mini-jack (M3) x 1		4-pole Mini-jack (M3) x 1	
VI-D Out	DVI-D 24-pin x 1 (DVI Revision 1.0		DVI-D 24-pin x 1 (DVI Revision 1.0	
'C In	Mini D-Sub 15-pin x1 (DDC2B compatible)		Mini D-Sub 15-pin x 1	
Audio In (L/R)	4-pole Mini-jack (M3) x 1 (S		4-pole Mini-jack (M3) x 1 (Shared with DVI-D/AV In)	
udio Out (L/R)	Stereo Mini-jack (M3) x 1		Stereo Mini-jack (M3) x 1	
erial In/Out	D-Sub 9-pin x 1/D-Sub 9-pin x 1, RS-232C Compatible		D-sub 9-pin x 1/x 1, RS-232C Compatible	
DIGITAL LINK	RJ45 x 1, 100BASE-TX, Compatible with PJLink™ 1		RJ45 x 1, 100BASE-TX, Compatible with PJLink <sup>™</sup> for TH-49/43SF2W (Shared with LAN)	
AN	RJ45 x 1, 100BASE-TX, Compatible with PJLink™ for TH-65SF2E and TH-55SF2W (Shared with DIGITAL LINK)		RJ45 x 1, 100BASE-TX, Compatible with PJLink™ for TH-49/43SF2W (Shared with D	
R In/Out	Stereo Mini-jack (M3) x 1/ x 1		Stereo Mini-jac	:k (M3) x 1/ x 1
USB	USB TYPE A Connector x 1, DC 5V/1A (USB 3.0 is not supported)		USB TYPE A Connector x 1, DC 5	V/1A (USB 3.0 is not supported)
Function Slot	-	-		-
ower Requirements	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz
ower Consumption	155 W	115 W	110 W	95 W
ower Off Condition	Approx. 0.3 W	Approx. 0.3 W	Approx. 0.3 W	Approx. 0.3 W
and-by Condition	Approx. 0.5 W	Approx. 0.5 W	Approx. 0.5 W	Approx. 0.5 W
imensions (W x H x D)	1452 x 834 x 64 mm (57.2" x 32.9" x 2.5")	1234 x 710 x 46 mm (48.5" x 28.0" x 1.8" )	1098 x 634 x 46 mm (43.2" x 24.9" x 1.8")	965 x 559 x 46 mm (38.0" x 22.0" x 1.8")
arton Size (W x H x D)	1648 x 1076 x 280 mm (64.9" x 42.4" x 11.1")	1448 x 952 x 223 mm (57.0" x 37.5" x 8.8")	1292 x 883 x 203 mm (50.9" x 34.8" x 8.0")	1141 x 779 x 203 mm (44.9" x 30.7" x 8.0")
ezel Width	T/R/L: 9.5 mm (0.38"), B: 15.7 mm (0.62")	T/R/L: 9.5 mm (0.38"), B: 15.5mm (0.61")	T/R/L: 9.5 mm (0.38"), B: 15.5 mm (0.61")	T/R/L: 9.5 mm (0.38"), B: 15.5 mm (0.61")
Veight	Approx. 29.8 kg (65.7 lbs.)	Approx. 18.0 kg (39.7 lbs.)	Approx. 14.7 kg (32.4 lbs.)	Approx. 10.7 kg (23.6 lbs.)
iross Weight	Approx. 41.0 kg (90.4 lbs.)	Approx. 26.0 kg (57.3 lbs.)	Approx. 21.0 kg (46.3 lbs.)	Approx. 15.0 kg (33.1 lbs.)
tch for Wall-Hanging	VESA Compliant 400 x 400 mm (15.8" x 15.8")	VESA Compliant 400 x 400 mm (15.8" x 15.8")	VESA Compliant 400 x 400 mm (15.8" x 15.8")	VESA compliant 400 x 400 mm (15.8" x 15.8")
uilt-in Speakers	20W [10 W + 10 W]	20 W [10 W + 10 W]	20 W [10 W + 10 W]	20 W [10 W + 10 W]
)rientation*1	Landscape/Portrait (Angle adjustment 0 - 45 degrees for both left and right with landscape setting. When installing the portrait setting, be sure that the Power Indicator comes to the upside.)		Landscape/Portrait (Angle adjustment 0 - 45 degrees for both left and right with landscape setting. When installing the portrait setting, be sure that the Power Indicator comes to the upside.)	
ïlting Angle* <sup>1</sup>	Landscape setting: 0 - 45 degrees forward/backward Portrait setting: 0 - 45 degrees forward/backward		Landscape setting: 0 - 45 degrees forward/backward Portrait setting: 0 - 45 degrees forward/backward	
perating Environment	Temperature: 0 °C to 40 °C (32°F to 104°F) /		Temperature: 0 °C to 40 °C (32°F to 104°F)*3 : 0 °C to 35 °C (32	
orage Environment	Temperature: -20 °C to 60 °C (-4 °F to 140 °F)*2 / Humidity: 20 % to 80 % (Non Condensation)		Temperature: -20 °C to 60 °C (-4 °F to 140 °F) /	'Humidity: 20 % to 80 % (Non-condensation)
perating Time <sup>*5</sup>	24 h/day		24 h	,
edestal	TY-ST55PE9	TY-ST55PE9	TY-ST43PE9	TY-ST43PE9
/all-hanging Bracket	_	_	_	_
Pigital Interface Box	_	-	-	_
IGITAL LINK Switcher	_	_	-	—
arly Warning Software*6	ET-SWA100	ET-SWA100 Series	ET-SWA100 Series	ET-SWA100
uto Display Adjustment Upgrade Kit*7	TY-VUK10	TY-VUK10	TY-VUK10	TY-VUK10

\*1: Please contact your sales representative with regard to the tilt angle before installation. Note that a gap of 0.5 mm or more is required when installing multiple displays.

\*2: If the temperature is 40 °C to 60 °C (104 °F to 140 °F), please keep in humidity 20 % to 40 %. \*3: for up to 1400 m (4593 ft) altitude

\*4: for between 1400 m (4593 ft) and 2800 m (9186 ft) altitude

Depending on the temperature or humidity conditions, uneven brightness may be observed. This is not a malfunction. This unevenness will disappear while applying current continuously. If not, consult the distributor.

\*5: In case of long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain on the screen. However, image retention can gradually disappear by displaying a moving images.

\*6: Suffix of the part number may differ depending on the license type.

\*7: Download the latest Video Wall Manager from PASS in advance. (https://panasonic.net/cns/prodisplays/pass/)

\*8: The availability varies depending on the country.

#### Standard

#### **FF1** Series 75' 65" TH-84EF1 TH-75EF1 TH-65EF1 **TH-32EF1** Model no. Screen Size (Diagonal)/Aspect Ratio 84-inch (2134 mm)/16:9 75-inch (1892 mm)/16:9 65-inch (1638 mm)/16:9 32-inch (801 mm)/16:9 IPS Panel/E-LED VA Panel/D-LED Panel Type IPS Panel/E-LED IPS Panel/D-LED PANE Effective Display Area (W x H) 1860 x 1046 mm (73.2" x 41.1") 1649 x 927 mm (65.0" x 36.5") 1428 x 803 mm (56.2" x 31.6") 698 x 392 mm (27.4" x 15.4") Resolution (H x V) 1920 x 1080 1920 x 1080 1920 x 1080 1920 x 1080 Brightness (Typ) 350 cd/m 410 cd/m<sup>2</sup> 350 cd/m<sup>2</sup> 350 cd/m<sup>2</sup> Contrast Ratio 1400:1 1200:1 4000:1 1400:1 **Response Time** 5.0 ms (G to G) 8 ms (G to G) 8 ms (G to G) 8 ms (G to G) Viewing Angle (Horizontal/Vertical) 178°/178° (CR≥10) 178°/178° (CR≥10) 178°/178° (CR≥20) 178°/178° (CR≥10) Panel Surface Treatment Anti-Glare (Haze 10 %) Anti-Glare (Haze 3 %) Anti-Glare (Haze 2 %) Anti-Glare (Haze 1 %) VIDEO In 4-pole Mini Jack (M3) x 1 4-pole Mini Jack (M3) x 1 Audio In(L/R) HDMI In HDMI TYPE-A Connector x 2\* \*VIERA LINK is not supported HDMI TYPE-A Connector x 2\* \*VIERA LINK is not supported. Component/RGB In Audio In (I /R) DVI-D In DVI-D 24-pin x 1 DVI-D 24-pin x 1 Audio In (L/R) Stereo Mini Jack (M3) x 1 (Shared with PC In) Stereo Mini Jack (M3) x 1 (Shared with PC In) PC In Mini D-sub 15-pin x 1 Mini D-sub 15-pin x 1 Audio In (L/R) Stereo Mini Jack (M3) x 1 (Shared with DVI-D In) Stereo Mini Jack (M3) x 1 (Shared with DVI-D In) PC Out USB TYPE A USB Connector DC 5V/1A (USB 3.0 is not supported.) TYPE A USB Connector DC 5V/1A (USB 3.0 is not supported.) Serial In D-sub 9-pin x 1, RS-232C Compatible D-sub 9-pin x 1, RS-232C Compatible DIGITAL LINK IR In/Out Mini Jack (M3) x 1 / x 1 Mini Jack (M3) x 1 / x 1 RJ45 x 1 10BASE-T/100BASE-TX. Compatible with PJLink™ RJ45 x 1 10BASE-T/100BASE-TX. Compatible with PJLink™ LAN Function Slot Power Requirements 220-240 V AC, 50 Hz/60 Hz Power Consumption 285 W 175 W 535 W 65 W Power off Condition Approx. 0.3 W Approx. 0.3 W Approx. 0.3 W Approx. 0.3 W Stand-by Condition Approx. 0.5 W Approx. 0.5 W Approx. 0.5 W Approx. 0.5 W Dimensions (W x H x D) 1910 x 1102 x 78 mm (75.2" x 43.4" x 3.1") 1681 x 959 x 77 mm (66.2" x 37.8" x 3.02") 1459 x 835 x 82 mm (57.5" x 32.9" x 3.3") 727 x 426 x 64 mm (28.7" x 16.8" x 2.5") Carton Size (W x H x D) 2059 x 1369 x 361 mm (81.1" x 53.9" x 14.3") 1831 x 1227 x 361 mm (72.1" x 48.3" x 14.3") 1655 x 1078 x 280 mm (65.2" x 42.5" x 11.1") 818 x 547 x 139 mm (32.2" x 21.6" x 5.5") Bezel Width 22.6 mm (0.89") (L/R), 25.6 mm (1.01") (T/B) 14.8 mm (0.58") (L/R/T/B) 13.9 mm (0.55") (L/R/T), 14.9 mm (0.59")(B) 11.9 mm (0.5") (L/R/T), 17.2 mm (0.7") (B) Weight Approx. 70.0 kg (154.3 lbs.) Approx. 55.0 kg (121.3 lbs.) Approx. 24.0 kg (52.0 lbs.) Approx. 5.3 kg (11.7 lbs.) Gross Weight Approx. 106.0 kg (233.7 lbs.) Approx. 85.0 kg (187.4 lbs.) Approx. 35.0 kg (77.2 lbs.) Approx. 8.0 kg (17.7 lbs.) Pitch for Wall-Hanging VESA compliant 600 x 500 mm (23.6" x 19.7") VESA compliant 600 x 400 mm (23.6" x 15.8") VESA compliant 400 x 400 mm (15.8" x 15.8") VESA compliant 100 x 100 mm (3.9" x 3.9") 20 W [10W + 10 W] (10% THD) 20 W [10W + 10 W] (10% THD) Built-in Speaker 20 W [10W + 10 W] (10% THD) 20 W [10W + 10 W] (10% THD) External Speaker Orientation Landscape/Portrait Landscape Landscape/Portrait Landscape/Portrait Tilting Angle 0-15 degrees forward with landscape setting\*2 0-20 degrees forward with landscape setting\*2 0-20 degrees forward with landscape setting\*2 0-20 degrees forward with landscape setting\*2 Temperature: 0 °C to 40 °C (32 °F to 104 °F)\*3 / Humidity: 20 % to 80 % (Non Condensation)\*4 Temperature: 0 °C to 40 °C (32 °F to 104 °F)\*3 / Humidity: 20 % to 80 % (Non Condensation)\*4 **Operating Environment** Storage Environment Temperature: -20 °C to 60 °C (-4 °F to 140 °F)\*3 / Humidity: 20 % to 80 % (Non Condensation)\*4 Temperature: -20 °C to 60 °C (-4 °F to 140 °F)\*3 / Humidity: 20 % to 80 % (Non Condensation)\*4 Operating Time\*5 16 h/dav 16 h/dav TY-ST32PE1 Pedestal Early Warning Software\*6 ET-SWA100 Series ET-SWA100 Series ET-SWA100 Series ET-SWA100 Series

\*1: Due to the terminal block construction, some connection cables and USB memory devices cannot be used. Be sure to check the "CONNECTION TERMINAL" information in the product specification sheet

84'

For more information about product specifications, please visit: http://panasonic.net/prodisplays/download/specsheets02.html

\*2: Please contact your sales representative with regard to the tilt angle before installation.

\*3: Environmental temperature to use this unit at high altitudes 1400 m (4393 ft) and higher and below 2800 m (9186 ft) above sea level): 0 °C to 35 °C (32 °F to 95 °F).

\*4: Depending on the temperature or humidity conditions, uneven brightness may be observed. This is not a malfunction. • This unevenness will disappear while applying current continuously. If not, consult the distributor

\*5: In case of long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain on the screen. However, image retention can gradually disappear by displaying a moving images.

\*6: Suffix of the part number may differ depending on the license type.

### LFE8 Series





43"

Model no.		TH-55LFE8	TH-48LFE8	TH-43LFE8
Screen Size (	(Diagonal)/Aspect Ratio	55-inch (1387 mm)/16:9	48-inch (1209 mm)/16:9	43-inch (1079 mm)/16:9
– Panel Type		IPS Panel/D-LED	VA Panel/D-LED	VA Panel/D-LED
□ Panel Type □ Effective Disp □ Resolution (H	play Area (W x H)	1209 x 680 mm (47.6" x 26.8")	1054 x 592 mm (41.5" x 23.3")	940 x 529 mm (37.0" x 20.8")
Resolution (H	H x V)	1920 x 1080	1920 x 1080	1920 x 1080
> Brightness (1	Typ]	350 cd/m <sup>2</sup>	350 cd/m <sup>2</sup>	350 cd/m <sup>2</sup>
Brightness (T Contrast Ration Response Tir Viewing Angl	io	1200:1	4000:1	3000:1
Response Tir	me	9 ms (G to G)	8 ms (G to G)	6.5 ms (G to G)
Viewing Angl	e (Horizontal/Vertical)	178°/178° (CR≥20)	178°/178° (CR≥20)	178°/178° (CR≥10)
Panel Surfac	e Treatment	Anti-Glare (Haze 1 %)	N/A	N/A
VIDE0 In		4-pole Mini .	Jack (M3) x 1	4-pole Mini Jack (M3) x 1
Audio In(L/R)	]	-	-	
HDMI In		HDMI TYPE-A Connector x 2*	*VIERA LINK is not supported.	HDMI TYPE-A Connector x 2* *VIERA LINK is not supported.
Component/F	RGB In	-	-	-
Audio In (L/R	?]	-	-	_
DVI-D In		DVI-D 24	4-pin x 1	DVI-D 24-pin x 1
DVI-D In Audio In (L/R PC In Audio In (L/R Audio In (L/R PC Out	2]	Stereo Mini Jack (M3)	x 1 (Shared with PC In)	Stereo Mini Jack (M3) x 1 (Shared with PC In)
PC In		Mini D-sub		Mini D-sub 15-pin x 1
Audio In (L/R				Stereo Mini Jack (M3) x 1 (Shared with DVI-D In)
PC Out	•		-	
USB		TYPE A USB Connector 5V DC/	/14 (USB 3.0 is not supported.)	TYPE A USB Connector 5V DC/1A (USB 3.0 is not supported.)
Serial In		D-sub 9-pin x 1, RS		D-sub 9-pin x 1, RS-232C Compatible
DIGITAL LINE	ĸ	5 5 6 6 7 pirx 1, 10	_	
LAN	i v	RJ45 x 1 10BASE-T/100BASE-TX, Compatible with PJLink™		RJ45 x 1 10BASE-T/100BASE-TX, Compatible with PJLink™
Function Slot	t	K343 X 1 10DA3E-1/100DA3E		
Power Requi		220-240 V AC, 50 Hz/60 Hz	220-240 V AC. 50 Hz/60 Hz	220-240 V AC. 50 Hz/60 Hz
Power Consu		170 W	150 W	135 W
Power off Co		Approx. 0.3 W	Approx. 0.3 W	Approx. 0.3 W
Stand-by Cor		Approx. 0.5 W	Approx. 0.5 W	Approx. 0.5 W
Dimensions (		1239 x 712 x 62 mm (48.8" x 28.0" x 2.5")	1082 x 624 x 62 mm [42.6" x 24.6" x 2.5"]	969 x 560 x 61 mm (38.2" x 22.1" x 2.4")
Carton Size		1365 x 864 x 185 mm [53.7" x 34.0" x 7.3"]	1192 x 773 x 171 mm (47.0" x 30.5" x 6.8")	1070 x 696 x 159 mm [42.2" x 27.4" x 6.3"]
Bezel Width		1365 X 864 X 185 mm (33.7 X 34.0 X 7.3 ) 12.6 mm (0.5") (L/R/T), 14.5 mm (0.6") (B)	11.9 mm (0.5") (L/R/T), 14.7 mm (0.6") (B)	10/0 x 6/6 x 15/ mm (42.2 x 2/.4 x 6.3 ) 11.9 mm (0.5") [L/R/T], 14.9 mm (0.6") [B]
Weight		Approx. 16.0 kg (35.3 lbs.)	Approx. 11.5 kg (25.4 lbs.)	Approx. 8.7 kg (19.2 lbs.)
Gross Weight Pitch for Wal		Approx. 24.0 kg (53.0 lbs.) VESA Compliant 400 x 400 mm (15.8" x 15.8")	Approx. 17.0 kg (37.5 lbs.)	Approx. 14.0 kg (30.9 lbs.) VESA Compliant 200 x 200 mm (7.9" x 7.9")
7	5 5	20 W [10W + 10		20 W [10W + 10 W] (10% THD)
Built-in Spea		20 W [10W + 10	W] (IU% IHD)	20 W [10W + 10 W] [10% THD]
External Spe	aker	- Landscap	- (Dentracit	Landscape/Portrait
Orientation		0-20 degrees forward w	-	
Tilting Angle		U-20 degrees forward w	vitn landscape setting*2	0-20 degrees forward with landscape setting*2
Operating En		Temperature: 0 °C to 40 °C (32 °F to 104 °F)*3	/ Humidity: 20 % to 80 % (Non Condensation)*4	Temperature: 0 °C to 40 °C (32 °F to 104 °F)*3 / Humidity: 20 % to 80 % (Non Condensation)*4
Storage Envi	ronment	Temperature: -20 °C to 60 °C (-4 °F to 140 °F)*3	<sup>3</sup> / Humidity: 20 % to 80 % (Non Condensation)*4	Temperature: -20 °C to 60 °C (-4 °F to 140 °F)*3 / Humidity: 20 % to 80 % (Non Condensation)*4
Operating Tir	me*5	16 h	/day	16 h/day
Zedestal		TY-ST43PE8	TY-ST43PE8	TY-ST43PE8
E Farly Warnin	ng Software*6	FT-SWA100 Series	ET-SWA100 Series	FT-SWA100 Series

48"

\*1: Due to the terminal block construction, some connection cables and USB memory devices cannot be used. Be sure to check the "CONNECTION TERMINAL" information in the product specification sheet.

For more information about product specifications, please visit: http://panasonic.net/prodisplays/download/specsheets02.html \*2: Please contact your sales representative with regard to the tilt angle before installation.

\*3: Environmental temperature to use this unit at high altitudes (1400 m (4593 ft) and higher and below 2800 m (9186 ft) above sea level): 0 °C to 35 °C (32 °F to 95 °F).

\*4: Depending on the temperature or humidity conditions, uneven brightness may be observed. This is not a malfunction. • This unevenness will disappear while applying current continuously. If not, consult the distributor

\*5: In case of long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain on the screen. However, image retention can gradually disappear by displaying a moving images.

\*6: Suffix of the part number may differ depending on the license type.

### **LF** Series, **SF2** Series, **EF1** Series, **LFE8** Series

#### Easy Display of Images Optimized for the Display Content

Conventional display panels are preset with display modes such as Standard and Dynamic. The LF80/SF2/LF8 Series comes with an extensive display menu to let you select the most suitable mode for the content to be displayed and the viewing environment. You can select the best mode for the video source and the place of display.



Displays images suitable for Displays images with priority signage in a bright environment. on natural color reproduction.





LF80

Standard

the original

Displays images faithful to

Surveillance Granhic Displays images with reduced Suitable for PC input brightness and with priority on gradation.

DICOM\* Display images close to the DICOM Part 14 Gravscale Standard

SF2

SF2

SF2

SF2 LF8

\*Although the term "DICOM" is used, this product is not medical equipment. Do not use displayed images for medical purposes such as examination or diagnosis.

Fanless Design

environments

Standard models robust fanless design prevents

can be safely installed and operated in high-traffic

problems caused by the intake of dusty air. The displays

#### **Durability Operation**

 Built for Continuous 24/7 Operation Use of quality electronic components quarantees dependable 24-hour operation seven days a week, even in portrait orientation.

#### Failover and Failback Safeguards for Mission Critical Situations

The LF80/8 Series is equipped with a variety of signal input terminals. If the main video and audio signals are interrupted, the system immediately switches to alternative signals. This makes it ideal for mission critical control rooms and surveillance centers. If the main signals are restored, the original image is displayed.


\* The usable combinations of main and backup signals are limited. For details, see the LF80/8 product website



#### HDMI CEC Device Linking Supported

HDMI-CEC compatible devices can be connected to the display by an HDMI cable, enabling the basic operations (such as power ON/OFF) of the compatible devices to be controlled by the display's remote control. Power ON/OFF of the display can also be switched using only the remote control (or main unit buttons) of the HDMI-CEC compatible devices.


\* The control of all devices cannot be guaranteed.



#### **Customizable Original Screen**

An original image created by your company or other desired picture can be displayed when the unit is turned on and when there is no input signal. The image data for the original screen can be transferred and stored in the display unit via a USB memory. This function allows a company logo mark, brand image, etc., to be displayed when there is no input signal.

· Certain limitations apply to the format for original screen. Compatible with 1920 x 1080 resolution only.



Standard

84/75/65EF1

SF2

SF2

SF2

Copy installation data

EF1

LF80

Setting and set values of [Picture], [sound],


[Setup], [Position], and [Options] menus

Indoor

The display can be set up in either portrait or landscape orientation. Only the SF Series and TH-84/65EF1 can be set up in portrait orientation.

#### DIGITAL LINK Function Enables Simple Installation and Low System Costs

Using DIGITAL LINK makes it possible to transmit video, audio and control signals over a long distance (up to 150 m [492 ft]) with a single LAN cable\*1. Easy cabling also reduces labor during setup. This provides transmission of high-guality images and sounds, as well as remote control.



USB memory

Parent Display

\*1 When connected with the [Long reach] mode, the maximum transmission distance is 150 m (492 ft) In this case, the unit can receive the signals of up to 1080/60p. A CAT5e (STP) cable or higher is required. \*2 TH-65SF2E, SF2W model only

#### **Cloning Function Speeds Up Multiple Display Setup**


When installing multiple displays, the Cloning function lets you use a USB memory (or LAN network) to copy the settings of a parent display to other units, thus greatly shortening the setup time.

- · [Date & Time], [Network Settings], [LAN Settings] and Display ID cannot be copied.
- The Cloning function works only for displays with the same screen size

\* Only the SF2 Series can be copied using a LAN network.

#### USB Memory Network Settings

Using a USB memory device, the network setting can be made for multiple displays. Individual IP addresses for each unit are automatically set.



Data that can be copied



26

84/75/65EF1

SF2

84/75/65EF1

SF2

LF80

LF8

SF2

#### Simple Signage Operation with No STB

The display can automatically start showing pictures when a USB memory containing data is inserted. The display unit can be used as digital signage without a set-top box or PC. And the content can be displayed smoothly without including the black screen display. What's more, the order of content playback and playback time can be programmed Content can also be rewritten and multiple displays can be operated via LAN.\*

- If it is difficult to insert a USB memory due to installation conditions. use a commercially available extension cable
- Some files cannot be played back even if they are in the supported format Regarding restrictions see the operation manual
- \* Multi Monitoring & Control Software (free) is required.

#### Playback by one unit





One of up to four display units becomes the parent unit, and the other units display images in sync with the parent unit. This enables the display of images in perfect sync when the panels are arranged next to each other.

Version 3.0. please visit

#### Multi Monitoring & Control Software (free) Lets You Control Devices in Groups

This free Panasonic software enables you to monitor and control up to 2048 devices over a LAN network from a single PC. It facilitates the control of multiple devices used in a facility or store. Content can also be rewritten and multiple displays can be operated via LAN.

\* Downloadable from the following URL

#### Make Your Signage Easy with Panasonic Application

The SF2 Series features a USB Media Player function that allows easy signage playback. Content Management Software is an application software for scheduling digital signage playback on a computer.

#### Play Content Automatically with Scheduling Function

Content Management Software for PC Version 3.0 (free) enables easy playlist creation with media support including combinations of still and video images. You can set up schedules for playing and closing your media playlist at predetermined dates and times.



### SF2

SF2

LAN

EF1

LFE8

LFF8

INTRANET

Ionitoring Station PC with Multi

Monitorina &

Control Software

SF2



LF80

#### Applicable format

JPG, JPEG, JPE, BMP\* Motion Image AVI, MKV, ASF, WMV, TS, MTS, MP4, 3GP, MOV, FLV, F4V

\* BMP is supported only by the 65/75/84FE1, SF2 Series.

#### Simultaneous playback by multiple units



Monitoring & Control

Controls up to 2048 displays

https://panasonic.net/cns/prodisplays/download/software/

It also allows power ON/OFF to be set.

Plavlists and schedules created with Content Management Software can be transferred to displays with USB memory, microSD Card, or via LAN. Synchronized playback on multiple displays is also supported.

https://panasonic.net/cns/prodisplays/download/software/

Convenient Playlist and Schedule Syncing

For more information about Content Management Software



#### Timer-Programmable Switching of Device Connection

The timer function of the display unit can be used to change connected signal source devices at a desired time. This allows an easy change of displayed content according to the application or the progress of an event.



#### **Play USB Content Instantly**

Playing Full HD video, still images, and digital documents from USB storage devices couldn't be easier. Just insert a thumb drive into the USB port and start presenting without needing to connect a PC. The Memory Viewer app enables image\* (JPEG, BMP) and video\* (WMV, AVI, MOV, MP4, MPG) selection from handy thumbnail previews.

\* In some cases, files may not be viewable even if they are encoded in a supported format

#### Applicable format


Still Image	JPG, JPEG, JPE, BMP
Motion Image	AVI, MKV, ASF, MWV, GS, MGS, MP4, 3GP, MOV, FLV, F4V



#### Smooth Switching of Presenters

The SF2 Series, TH-84/75/65EF1 automatically switches source signals when the input signal for the current content stops or when an input signal other than the signal of the current content is received. When presenters change during a meeting, the displayed image can be switched easily by simply changing the cable connection, thus eliminating the need to operate the remote control.

\* Only analog (PC input)/digital (HDMI input or DVI-D input) signal switchover is supported. \* The 2 switching inputs must be set in advance.



#### Choose the Installation to Match Your Application

The LF80/SF2/LF8 series is designed for use in either portrait or horizontal orientation with no effect on panel color and lifespan, further reducing TCO. A tilt installation up to 45 degrees forward or backward is also possible. The angle can be adjusted for easy viewing when installed in a high location.

\* Angle adjustment is not possible for forward/backward tilting installation. Be sure that the Power Indicator comes to the downside.

\* The SF2 Series does not support angle adjustment for portrait installation.



## VF/LFV Series



55"

Model no.	TH-55VF1H	TH-55LFV70	
Screen Size (Diagonal)/Aspect Ratio	55-inch (1387mm)/16:9	55-inch (1387mm)/16:9	
Panel Type	IPS Panel/D-LED	IPS Panel/D-LED	
Effective Display Area (W x H)	1209 x 680 mm (47.6" x 26.7")	1209 x 680 mm (47.6" x 26.7")	
Resolution (H x V)	1920 x 1080	1920 x 1080	
Brightness (Typ)	700 cd/m <sup>2</sup>	700 cd/m <sup>2</sup>	
Contrast Ratio	1200:1	1200:1	
Dynamic Contrast Ratio	500000:1	500000:1	
Response Time	8.0 ms (G to G)	12 ms (G to G)	
Viewing Angle (Horizontal/Vertical)	178°/178° (CR≥10)	178°/178° (CR≥10)	
Panel Surface Treatment	Anti-Glare (Haze 44%)	Anti-Glare (Haze 44%)	
VIDEO In	BNC x 1 (Shared with Component In)	BNC x 1 (Shared with Component In)	
Audio In (L/R)	Pin Jack x 1 set (Shared with Component In)	Pin Jack x 1 set (Shared with Component In)	
HDMI In	HDMI Type A Connector x 1	HDMI Type A Connector x 1	
Component/RGB In	BNC x 1 set (Shared with VIDEO In)	BNC x 1 set (Shared with VIDEO In)	
Audio In (L/R)	Pin Jack x 1 set (Shared with VIDEO In)	Pin Jack x 1 set (Shared with VIDEO In)	
DVI-D In	DVI-D 24-pin x 2 (Female)	DVI-D 24-pin x 2 (Female)	
Audio In (L/R)	Stereo Mini Jack (M3) x 1 (Shared with PC In)	Stereo Mini Jack (M3) x 1 (Shared with PC In)	
DisplayPort In	DisplayPort x 1 (DP1.1 Dual Mode only)	DisplayPort x 1 (DP1.1 Dual Mode only)	
DVI-D Out			
DVI-I Out	_	_	
PC In	Mini D-sub 15-pin x 1 (Female)	Mini D-sub 15-pin x 1 (Female)	
Audio In (L/R)	Stereo Mini Jack (M3) x 1 (Shared with DVI-D In)	Stereo Mini Jack (M3) x 1 (Shared with DVI-D In)	
DIGITAL LINK In/DIGITAL LINK Out	RJ45 x 1/RJ45 x 1	RJ45 x 1/RJ45 x 1	
USB	USB Type A Connector (DC 5 V/0.5 A) x 1 (USB 3.0 is not supported.)	USB Type A Connector (DC 5 V/0.5 A) x 1 (Memory Viewer Only, USB 3.0 is not supported.)	
Audio Out (L/R)	Stereo Mini Jack (M3) x 1 set	Pin Jack x 1 set	
Serial In/Out	D-sub 9-pin x 1 (Male)/D-sub 9-pin x 1 (Male), RS-232C Compatible	D-sub 9-pin x 1 (Male)/D-sub 9-pin x 1 (Male), RS-232C Compatible	
IR In/Out	Stereo Mini-Jack (M3) x 1 / Stereo Mini-Jack (M3) x 1	Stereo Mini-Jack (M3) x 1 / Stereo Mini-Jack (M3) x 1	
LAN In/Out	RJ45 x 1/x 1 (100BASE-TX, Compatible with PJLink <sup>™</sup> ) (Shared with DIGITAL LINK)	RJ45 x 1/x 1 (100BASE-TX, Compatible with PJLink™) (Shared with DIGITAL LINK)	
Power Requirements	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz	
Power Consumption	300 W	330 W	
Stand-by Condition	Approx. 0.5 W	Approx. 0.5 W	
Dimensions (W x H x D)	1211.4 x 682.2 x 99 mm (47.7" x 26.9" x 3.9")	1213.4 x 684.2 x 95 mm (47.8" x 26.9" x 3.7")	
Carton Size (W x H x D)	1544 X 973 X 301 mm (60.8" X 38.3" X 11.9")	1551 X 961 X 450 mm (61.1" X 37.8" X 17.7")	
Bezel Width	0.9 mm (0.036") (T/R/L/B)	L/T: 2.25 mm (0.088"), R / B: 1.25 mm (0.049")	
Bezel to Bezel <sup>*1</sup>	1.8 mm (0.07") (Multi Screen)	3.5 mm (0.14") (Multi Screen)	
Weight	Approx. 25.0 kg (55.1 lbs.)	Approx. 30.0 kg (66.1 lbs.)	
Gross Weight	Approx. 34.0 kg (75.0 lbs.)	Approx. 46.0 kg (101.4 lbs.)	
Pitch for Wall-Hanging	VESA Compliant 400 x 400 mm (15.8" x 15.8")	VESA Compliant 400 x 400 mm (15.8" x 15.8")	
External Speaker	8 Ω, 20 W [10 W + 10 W] (10% THD)	8 Ω, 20 W [10 W + 10 W] (10% THD)	
Orientation*2	Landscape/Portrait	Landscape/Portrait	
Tilting Angle <sup>*2</sup>	Vertical Only	Vertical Only	
Operating Environment	Temperature: 0 °C to 40 °C (32 °F to 104 °F)*4 / 0 °C to 35 °C (32 °F to 95 °F)*5 / Humidity: 10 % to 90 % (Non-Condensation)	Temperature: 0 °C to 40 °C (32 °F to 104 °F)*3 / Humidity: 10 % to 90 % (Non Condensation)	
Storage Environment	Temperature: -20 °C to 60 °C (-4 °F to 140 °F) / Humidity: 10 % to 90 % (Non Condensation)	Temperature: -20 °C to 60 °C (-4 °F to 140 °F) / Humidity: 10 % to 90 % (Non Condensatio	
Operating Time <sup>*6</sup>	24 h/day	24 h/day	
Remote Control Kit	_	-	
Cover Frame Kit	TY-CF55VW1	TY-CF55VW50	
Installation Mount	TY-VK55LV1	TY-VK55LV1	
Early Warning Software*7	ET-SWA100 Series	ET-SWA100 Series	
Auto Display Adjustment Upgrade Kit*8	TY-VUK10	TY-VUK10	
Multi Window Processor*9	ET-MWP100G	ET-MWP100G	

\*1: Bezel-to-bezel distance means the combined top and bottom (or left and right) bezel width of adjacent displays in multi-screen configuration. The gap between

displays is not included. Note that a gap of 0.5 mm or more is required when installing multiple displays.

\*2: Please contact your sales representative with regard to the tilt angle before installation.

\*3: For up to 2000 m (6562 ft) altitude. \*4: For up to 1400 m (4593 ft) altitude. \*5: For between 1400 m (4593 ft) and 2800 m (9186 ft) altitude.

\*6: In case of long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain on

the screen. However, image retention can gradually disappear by displaying a moving images.

\*7: Suffix of the part number may differ depending on the license type.

\*8: Download the latest Video Wall Manager from PASS in advance. (https://panasonic.net/cns/prodisplays/pass/) \*9: The availability varies depending on the country.

### LFV Series

55"

		49"	55~
Model no.	TH-55LFV8	TH-49LFV8	TH-55LFV6
Screen Size (Diagonal)/Aspect Ratio	55-inch (1387 mm)/16:9	49-inch (1237 mm)/16:9	55-inch (1387 mm)/16:9
Panel Type	IPS Panel/D-LED	IPS Panel/D-LED	IPS Panel/D-LED
Effective Display Area (W x H)	1209.6 x 680.4 mm (47.6" x 26.8")	1077.7 x 607.9 mm (42.5" x 24.0")	1209 x 680 mm (47.6" x 26.7")
Effective Display Area (W x H) Resolution (H x V) Brightness (Tvn)	1920 x 1080	1920 x 1080	1920 × 1080
Brightness (Typ)	500 cd/m <sup>2</sup>	450 cd/m <sup>2</sup>	500 cd/m <sup>2</sup>
Contrast Ratio	1400:1	1300:1	1400:1
Dynamic Contrast Ratio	500000:1	500000:1	500000:1
Contrast Ratio Dynamic Contrast Ratio Response Time	12 ms (G to G)	8.0 ms (G to G)	12 ms (G to G)
Viewing Angle (Horizontal/Vertical)	178°/178° (CR≥10)	178°/178° (CR≥10)	178°/178° (CR≥10)
Panel Surface Treatment	Anti-Glare (Haze 10 %)	Anti-Glare Low-Reflection (Haze 3 %)	Anti-Glare (Haze 10 %)
VIDEO In	BNC x 1 (Shared w		
Audio In (L/R)	Stereo Mini-Jack (M3) x 1 (Sha		Stereo Mini Jack (M3) x 1 (Shared with Component/RGB In)
HDMI In	HDMI Type A		
Component/RGB In	BNC x 1 (Shared		-
Audio In (L/R)	Stereo Mini-Jack (M3) x		_
DVI-D In	DVI-D 24-pin		_
Audio In (L/R)	Stereo Mini Jack (M3)		
DisplayPort In/Out	DisplayPort x1 (Dp1.1a/DP1.2)		
			– DVI-D 24-pin x 1 (Female)
DVI-I Out	– DVI-I 29-pin	- x 1 (Female)	DVI-D 24-pin X 1 (Fernale)
DVI-D Out DVI-I Out PC In	Mini D-Sub 15-j		
Audio In (L/R)			
DIGITAL LINK In/DIGITAL LINK Out	Stereo Mini Jack (M3) x		
USB	USB Type A Connecto		USB Type A Connector (DC 5 V/1 A) x 1
	(USB 3.0 is no		(USB 3.0 is not supported.)
Audio Out (L/R) Serial In/Out	Stereo Mini-		
	2.5 mm stereo mini jack x 1/ 2.5 mm ste		D-Sub 9-pin x 1 (Male)/ x 1, RS-232C Compatible
IR In/Out	Stereo Mini-Jack (M3) x 1		
LAN In/Out	RJ45 x 1 (10BASE-T/100BASE-T)		RJ45 x 1 (10BASE-T/100BASE-TX, Compatible with PJLink™)/—
Power Requirements	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz
Power Consumption	320 W	220 W	210 W
Stand-by Condition	Approx. 0.5 W	Approx. 0.5 W	Approx. 0.5 W
Dimensions (W x H x D)	1213.4 x 684.2 x 95 mm (47.8" x 26.9" x 3.7")	1077.7 x 607.9 x 103.9 mm (42.5" x 24.0" x 4.1")	1213.4 x 684.2 x 95 mm (47.8" x 27.0" x 3.7")
Carton Size (W x H x D)	1544 x 973 x 301 mm (60.8" x 38.3" x 11.9")	TBD	1544 x 973 x 301 mm (60.8" x 38.3" x 11.9")
Bezel Width	L/T: 2.25 mm (0.088"), R / B: 1.25 mm (0.049")	L/T: 2.25 mm (0.088"), R / B: 1.25 mm (0.049")	L/T: 2.25 mm (0.089"), R / B: 1.25 mm (0.050")
Bezel to Bezel*1	3.5 mm (0.14") (Multi Screen)	3.5 mm (0.14") (Multi Screen)	3.5 mm (0.14") (Multi Screen)
Weight Gross Weight Pitch for Wall-Hanging	Approx. 30.0 kg (66.1 lbs.)	Approx. 22.0 kg (48.5 lbs.) TBD	Approx. 30.0 kg (66.1 lbs.)
Gross Weight	Approx. 40.0 kg (88.2 lbs.)	TBD	Approx. 40.0 kg (88.2 lbs.)
Pitch for Wall-Hanging	VESA Compliant 400 x 400 mm (15.8" x 15.8")	VESA Compliant 400 x 400 mm (15.8" x 15.8")	VESA Compliant 400 x 400 mm (15.8" x 15.8")
External Speaker	8 Ω, 20 W [10 W + 10 W] (10% THD)	8 Ω, 20 W [10 W + 10 W] (10% THD)	8 Ω, 20 W [10 W + 10 W] (10% THD)
Orientation*2	Landscape/Portrait	Landscape/Portrait	L andscape/Portrait
Tilting Angle <sup>*2</sup>	Vertical Only	Vertical Only	Vertical Only
Operating Environment	Temperature: 0 °C to 4 Humidity: 20 % to 80 9		Temperature: 0 °C to 40 °C (32 °F to 104 °F)*4 / 0 °C to 35 °C (32 °F to 95 °F)*5 / Humidity: 10 % to 90 % (Non-Condensation)
Storage Environment	Temperature: -20 °C to 60 °C (-4 °F to 140 °F)	/ Humidity: 5 % to 95 % (Non Condensation)	Temperature: -20 °C to 60 °C (-4 °F to 140 °F) / Humidity: 10 % to 90 % (Non Condensation)
Operating Time <sup>*5</sup>	24 h/day	24 h/day	24 h/day
Remote Control Kit	_	_	
Cover Frame Kit Installation Mount Early Warning Software*6 Auto Dirplay (dijustment Liperado Kit*7	TY-CF55VW1	_	TY-CF55VW50
Installation Mount	TY-VK55LV1	TY-VK49LV2	TY-VK55LV2
Early Warning Software*6	ET-SWA100 Series	ET-SWA100 Series	ET-SWA100 Series
Auto Display Adjustment Upgrade Kit*7	TY-VUK10 (up to ver1.7)	TY-VUK10 (up to ver1.7)	TY-VUK10
Multi Window Processor*8	ET-MWP100G	ET-MWP100G	ET-MWP100G

\*1: Bezel-to-bezel distance means the combined top and bottom (or left and right) bezel width of adjacent displays in multi-screen configuration. The gap between

displays is not included. Note that a gap of 0.5 mm or more is required when installing multiple displays.

\*2: Please contact your sales representative with regard to the tilt angle before installation.

\*3: For up to 2000 m (6562 ft) altitude. \*4: For up to 2800 m (9286 ft).

\*5: In case of long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain

on the screen. However, image retention can gradually disappear by displaying a moving images.

\*6: Suffix of the part number may differ depending on the license type.

\*7: Download the latest Video Wall Manager from PASS in advance. (https://panasonic.net/cns/prodisplays/pass/) \*8: The availability varies depending on the country.

#### Narrow Bezel for Seamless Video Walls

Narrow frames on Panasonic's LCD Video Wall Series reduce bezel-to-bezel distance to a near-invisible 1.8 mm\*. Even when viewed close-up, screen borders are almost indiscernible, resulting in truly spectacular large-format images.

\* TH-55VF1H features 1.8 mm (0.07"), TH-55LFV70/6/8/6 3.5 mm (0.14"), and TH-47LFV5 4.9 mm (0.19") bezel-to-bezel distance. Bezel-to-bezel distance refers to the combined top and bottom (or left and right) bezel-width of adjacent displays in video-wall configuration. The gap between displays is not included. Note that a gap of 0.5 mm or more is required when installing multiple displays


#### Improved Multi-Screen Video Visibility

When high-speed video is played on multiple screens in a video wall, some image misalignment can occur between vertically adjacent panels. VF1H and LFV6 Series feature a Reverse Scan Function that alternates the scanning direction of vertically adjacent displays to improve image alignment. Frame Control Function, meanwhile, adjusts the number of video frames displayed to reproduce images with natural fluidity.

Reverse Scan Function Reverses direction of image scanning to smoothly play enlarged video on multiple screens

Bezel-to-beze

distance



VF1H

1.8<sub>mm</sub>\* (0.07")

#### Note: Images are simulated.

4.9 mm (0.19")

VF1H

LFV6

VF1H

LFV70 LFV6 LFV8

VF1H


LFV70/60/8/6

3.5 mm (0.14")

#### Delivers Stable Brightness for Up to 8 Years\*

The VF1H Series incorporates Long Life mode and a new Auto Brightness Adjustment function. In Long Life mode, backlight brightness is optimized to extend product life. Auto Brightness Adjustment function corrects light output automatically according to the rate of backlight deterioration to maintain constant brightness for longer.

\* Figure is approximate when operating continuously for 24 hours x 365 days.



Long Life mode & Auto Brightness Adjustment function

Auto brightness adjustment : Of Note: Assuming operating conditions of 25 °C (± 2 °C). Environmental conditions and conditions of usage may affect

brightness longevity and operating period. "On2" delivers approximately 60 % maximum specified backlight brightness. Auto brightness adjustment cannot be turned on if panel illumination period has exceeded 1,000 hours. Note: Images and graphs are simulated.

#### Failover and Failback Safeguards Maintain Image Display

100%

Appro 60%

Appro

3096

50%

Digital signal inputs comprise one or two DVI-D terminals together with HDMI. DisplayPort, DIGITAL LINK\*, and USB terminals. If primary audio-video signals are interrupted, the display immediately switches to an alternative input. This makes the Panasonic LCD Video Wall Series (except LFV8) well suited for use in control rooms and in other applications where uninterrupted playback is essential.

\* DIGITAL LINK available on VF1H and LFV70 only. Display Port available on LFV70 only.



If AV signals via the primary input is interrupted, images are no longer displayed.

If the primary AV signal is interrupted, the system automatically switches to a backup input so video display is maintained

VF1H

Failover and Fai

LFV70

#### DIGITAL LINK Simplifies Installation at Lower Cost


Based on HDBaseT<sup>™</sup> technology, the DIGITAL LINK connection on VF1H and LFV70 Series displays supports audio, video, and control signal transmission over long distances, and can also be used to daisy-chain multiple displays via a single cable. This eliminates the need for video splitters and other routing devices. The LFV60/6/8/5 Series, meanwhile, supports daisy chain via DVI with separate video and control (serial or IR) connections. Note: CAT5e or higher STP cable required.

#### DIGITAL LINK Reduces Cabling Cost and Complexity DisplayPort DVI I AN Control BS-232C IR DIGITAL LINK Combines AV and Control Signal Save time and money with Panasor simplified DIGITAL LINK connection

#### Installation Frame Simplifies Set-up

The optional Installation Mount makes it much easier to configure a video wall. There's no need for complicated display positioning, and fluctuations between installers are covered. It also saves time and cuts labor costs.

Video wall fluctuations occur when the bezels are not correctly aligned vertically and horizontally and the surfaces are not properly adjusted. Installation is guick and easy using the rigid frame, with easy adjustment using surface alignment magnets. This structure also makes the displays easier to remove when performing maintenance. \*Landscape setting only.



The rigid frame is connected. so there is no need for positioning adjustment

LFV6

LFV8

LFV70

LFV70

VF1H

VF1H

LFV70

VF1H

Automatic adjustment by surface alignment magnets suppresses surface shifting. \*For 55-inch TY-VK55LV1 For 49-inch TY-VK49I V2 For 47-inch TY-VK47IV1

LFV6

LFV8

#### Video Wall Manager Software and Auto Display Adjustment Upgrade Kit

Panasonic's free Video Wall Manager software can be used with LCD Video Wall Series displays. With this software, you can calibrate display color using a color sensor\*1 (optional), adjust display settings, and control and manage data via PC. If you upgrade this software with an optional TY-VUK10 Auto Camera Adjustment Kit, you can adjust brightness and color among multiple displays automatically using a compatible camera (Nikon D5200/D5300/D5500)\*2.

\*1 LFV8 series are not compatible with calibration using a color sensor.

2 Available only with normal zoom lens: AF-5 DX NIKKOR 18-55 mm f/3.5-5.6G VR. AF-5 DX NIKKOR 18-140 mm f/3.5-5.6G ED VR. AF-5 DX NIKKOR 18-55 mm f/3.5-5.6G VR II

#### With LFV70 and TY-VUK10 connected



Auto Display Adjustment Upgrade Kit: http://business.panasonic.co.uk/visual-system/ty-vuk10-features

#### Other Features

 Optimized Image Modes\* (VF1H/LFV6 Series only) High-Performance Imaging Engine\* (VF1H/LFV6 Series only)

\* More information, please see page 24.

### LFX Series



_	Model no.	TH-47LFX60	TH-47LFX6N
	Screen Size (Diagonal)/Aspect Ratio	47-inch (1192 mm)/16:9	47-inch (1192 mm)/16:9
	Panel Type	IPS Panel/D-LED	IPS Panel/D-LED
ΕĽ	Effective Display Area (W x H)	1039 x 584 mm (40.9" x 23.0")	1039 x 584 mm (40.9" x 23.0")
⊿ N	Resolution (H x V)	1920 x 1080	1920 x 1080
٩	Brightness (Typ)	2000 cd/m <sup>2</sup>	1200 cd/m <sup>2</sup>
AΥ	Contrast Ratio	1300:1	1300:1
DISPLAY PAN	Dynamic Contrast Ratio	500000:1	500000:1
1S	Response Time	10 ms (G to G)	10 ms (G to G)
	Viewing Angle (Horizontal/Vertical)	178°/178°	178°/178°
	Panel Surface Treatment	N/A	N/A
	VIDEO In		-
	Audio In (L/R)	-	-
	HDMI In	HDMI Type A	Connector x 1
	Component/RGB In		
	Audio In (L/R)	-	-
ERMINAL	DVI-D In	DVI-D 24	
Σ	Audio In (L/R)	Stereo Mini Jack (M3)	•••••••••••••••••••••••••••••••••••••••
ш	PC In	Mini D-Sub 15-	
$\vdash$	Audio In (L/R)	Stereo Mini Jack (M3) x	
	Audio Out (L/R)	Pin Jack	
	DIGITAL LINK	RJ45 x 1 (Sha	•
	Serial In	D-Sub 9-pin x 1, RS	
	LAN Power Requirements	RJ45 x 1 100BASE-TX, Compatible with	
	Power Consumption	220-240 V AC, 50 Hz/60 Hz 370 W	220-240 V AC, 50 Hz/60 Hz 270 W
	Power Off Condition	Approx. 0.3 W	Approx. 0.3 W
	Stand-by Condition	Approx. 0.5 W	Approx. 0.5 W
	Outdoor Mode On	Approx. 41 W	Approx. 6.5 W
	Network Stand-by Mode	Approx. 41 W Approx. 16 W	Approx. 16 W
	Dimensions (W x H x D)	1162 x 706 x 216 mm [45.8" x 27.8" x 8.5"]	1162 x 706 x 216 mm (45.8" x 27.8" x 8.5")
	Carton Size (W x H x D)	1308 x 851 x 323 mm (51.5" x 33.5" x 12.7")	1308 x 851 x 323 mm (51.5" x 33.5" x 12.7")
SAL	Weight	Approx. 47.0 kg (103.0 lbs.)	Approx. 47.0 kg (103.0 lbs.)
ш	Gross Weight	Approx. 55.0 kg (121.0 lbs.)	Approx. 55.0 kg (121.0 lbs.)
ENERAL	Pitch for Wall-Hanging		VESA Compliant 400 x 400 mm (15.8" x 15.8")
G	Built-in Speakers	-	-
	Direct Sunlight Capability	Yes (Built-in Air	Cooling System)
	Dust and Water Resistant Level	IP55 Eq	uivalent
	Orientation	Landscap	e/Portrait
	Tilting Angle	0-20 degrees forward with landscape and portrait se	tting / 0-20 degrees backward with portrait setting*1
	Operating Environment*2		F) / Humidity: 20 % to 80 % (Non Condensation)
	Storage Environment	Temperature: -20 °C to 60 °C (-4 °F to 140 °F)	/ Humidity: 20 % to 80 % (Non Condensation)
	Operating Time*4	24 h	/day
S	Replacement Air Filter	TY-AF60STD	TY-AF60STD
	Digital Interface Box	ET-YFB100G	ET-YFB100G
NO	J		
OPTIONS	DIGITAL LINK Switcher Early Warning Software*5	ET-YFB200G	ET-YFB200G ET-SWA100 Series

\*1: Please contact your sales representative with regard to the tilt angle before installation. \*2: Don't use in places where the presence of corrosive gases or salt damage area. \*3: When used in Outdoor mode. \*4: In case of long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain on the screen. However, image retention can gradually disappear by displaying a moving images. \*5: Suffix of the part number may differ depending on the license type.



#### High-Brightness 2000-cd/m<sup>2</sup> Model with Wide-Viewing-Angle IPS Panel and LED Backlight

Images are clear even in brightly lit places. Full 2000 cd/m<sup>2+</sup> brightness maintains excellent visibility under direct sunlight. This makes the LFX ideal for installation in drive-through lanes. And because the brightness isn't affected by external light, information such as menu items and prices remain clear and easy to read. \* TH-47LFX60 only.

#### Forced Air-Cooling System Helps to Prevent Blackouts and Dew Condensation

Outside air is brought into the cabinet to produce an airflow between the front glass and the LCD panel. This suppresses internal

temperature rises and prevents blackouts when the display is installed outdoors. It also serves as a countermeasure against condensation.



Direct sunlight raises the LCD panel temperature and causes blackouts. Inder direct sunlight.

#### Highly Durable Display Resists Temperature Changes and the Summer Sun

Featuring an operating temperature range of -20°C\*1 to 50°C (-4 °F\*1 to 122 °F), performance remains unchanged even in cold and hot climates.

\*1: When used in Outdoor mode.

#### DIGITAL LINK for Transmission of Video, Audio and Control Signals for up to 100m (328 ft) with a Single LAN Cable

Only a single LAN cable<sup>\*1</sup> is required to transmit uncompressed HD video, audio and control signals for a distance of up to 100m [328 ft]. This enables indoor installation of the PC and other devices connected to the display at an outdoor location in order to protect the PC and devices from rain and dust. Since only one cable needs to be connected between the PC and panel, cable routing work is quick and easy. Because a control signal can also be sent simultaneously, it is easy to upgrade the system by combining it with the optional DIGITAL LINK Switcher [ET-YFB200G]/Digital Interface Box (ET-YFB100G).

\*1: Use an STP cable of CAT5e or higher. \*2: WUXGA (1920 × 1200 pixels) compatible.

#### 🕩 Outdoor

#### Aluminum Cabinet and Tempered Glass

The aluminum cabinet strongly resists corrosion. In addition, tempered glass ensures rugged strength against impacts.



#### High Reliability Enables Continuous 24-Hour Operation

The use of a highly durable panel and electronic components allows continuous 24-hour operation, ideal for installation in 24/7 stores, drive-thrus, public places, etc.

#### Supporting Stable Operation — Early Warning Software (ET-SWA100)

Early Warning Software monitors the status of display connected to an intranet and Informs you when an abnormality is detected or predicted, and when there are symptoms of trouble. The minimizes display downtime to support more stable operation.

Do io and ODM no fo the display ct the ce only be the ick and Digital Digi

### BF1 Series



	Model no.	TH-80BF1	TH-65BF1
	Screen Size (Diagonal)/Aspect Ratio	80-inch (2032 mm)/16:9	65-inch (1638 mm)/16:9
EL	Panel Type	VA Panel/E-LED	VA Panel/E-LED
AN	Effective Display Area (W x H)	1771 x 996 mm (69.7" x 39.2")	1428 x 803 mm (56.2" x 31.6")
P	Resolution (H x V)	1920 x 1080	1920 x 1080
A	Brightness (Typ)	350 cd/m <sup>2</sup>	350 cd/m <sup>2</sup>
SPL	Contrast Ratio/Dynamic Contrast Ratio	5000:1/50000:1	4000:1/50000:1
DISPLAY PANEL	Response Time	4 ms (G to G)	6.5 ms (G to G)
	Viewing Angle (Horizontal/Vertical)	176°/176° (CR≥10)	178°/178° (CR≥10)
OUCH PAVEL	Detection Method	Infrared Blocking Detection Method	Infrared Blocking Detection Method
LOUO1	Touch Operation	Up to 12-point multi-touch*1	Up to 12-point multi-touch*1
	VIDEO In	BNC	x1
	Audio In (L/R)	Stereo Mini Jack (M3) x 1 (Sha	red with Component/RGB In)
	HDMI In	HDMI Type A	Connector x 2
	Component/RGB In	BNC x	1 set
	Audio In (L/R)	Stereo Mini Jack (M3) x 1	1 (Shared with VIDEO In)
_	DVI-D In	DVI-D 24-pir	n (Digital) x 1
A A	Audio In (L/R)	Stereo Mini Jack (M3)	x 1 (Shared with PC In)
TERMINAL	PC In	Mini D-Sub 15-pin x1 (Female	e), Plug & Play (VESA DDC 2B)
ERI	Audio In (L/R)	Stereo Mini Jack (M3) x	1 (Shared with DVI-D In)
$\vdash$	PC Out	Mini D-Sub	o 15-pin x1
	USB A	TYPE A USB Connector >	< 1 (For Memory Viewer)
	USB B	TYPE B USB Connector	r × 1 (For Touch Panel)
	Serial In	D-Sub 9-pin x 1 for external of	control, RS-232C Compatible
	DIGITAL LINK		red with LAN)
	LAN		h PJLink™ (Shared with DIGITAL LINK)
	Function Slot		1 (Vacant)
	Power Requirements	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz
	Power Consumption	350 W	215 W
	Power Off Condition/Stand-by Condition	Approx. 0.3 W/Approx. 0.5 W	Approx. 0.3 W/Approx. 0.5 W
	Dimensions (W x H x D)	1868 x 1093 x 104 mm (73.6" x 43.1" x 4.1")	1517 x 892 x 108 mm (59.8" x 35.2" x 4.3")
	Carton Size (W x H x D)	2075 x 1319 x 404 mm (81.7" x 52.0" x 16.0")	1720 x 1027 x 286 mm (67.8" x 40.5" x 11.3")
	Weight	Approx. 81.0 kg (178.6 lbs.)	Approx. 58.0 kg (127.9 lbs.)
	Gross Weight	Approx. 99.0 kg (219.0 lbs.)	Approx. 68.0 kg (150.0 lbs.)
	Pitch for Wall-Hanging	VESA Compliant 400 x 400 mm (15.8" x 15.8")	684 x 300 mm (26.9" x 11.8")
۹L	Protective Glass Thickness	Approx. 3.3 mm (0.13")/Anti-glare (Haze 10%)	Approx. 2.9 mm (0.12")/Anti-glare (Haze 10%)
ER,	Built-in Speaker	20 W [10 W + 10 W] (10 % THD)	20 W [10 W + 10 W] (10 % THD)
GENERAL	External Speaker Orientation	8 Ω, 20 W [10 W + 10 W] (10 % THD)	8 Ω, 20 W [10 W + 10 W] (10 % THD) ng the display on portrait setting,
ט	Chemation		licator at the topside of the display.)
	Tilting Angle	0-20 degrees with landscape setting	Up to 45 degrees backward in landscape orientation
	Operating Environment		1400 m (4593 ft) altitude] / 0 °C to 35 °C (32 °F to 95 °F) Ititude], Humidity: 20 % to 80 % (Non-condensation)
	Storage Environment		Humidity: 20 % to 80 % (Non-condensation)
	Operating Time*2		/day
	Built-in wireless LAN function: Standard	2.4 GHz: IEEE802.11b/g /r	
	Infrastructure Mode	WPA2-PSK (TKIP/AES), WPA-PSK (TKIP/AES),	
			GTC] /EAP-TTLS [MD5/MS-CHAPv2], 128-bit/64-bit)
	Pedestal	TY-ST65P20	TY-ST65P20
	Mobile Stand	TY-ST80LF70	TY-ST65PB2
NS N	Wall-hanging Bracket	-	TY-WK65PR20 (Vertical)
OPTIONS	Ceiling-hanging Bracket	_	-
μ	Easy Wireless Stick*3	ET-UW100	ET-UW100
0	Digital Interface Box	ET-YFB100G	ET-YFB100G
	DIGITAL LINK Switcher*4	ET-YFB200G	ET-YFB200G
	Early Warning Software*5	ET-SWA100 Series	ET-SWA100 Series

\*1 When using the Whiteboard Software for Windows<sup>®</sup>. Up to 4-point using the Built-in Whiteboard Software and Whiteboard Software for Mac.

\*2 In case running for a long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain on the screen. However, image retention can gradually disappear by displaying a moving images.

\*3 This product can be purchased in the U.S., Canada, Japan, Australia, and New Zealand.

38

\*4 Long Reach Mode on ET-YFB200G is not supported. \*5 Part number suffix may differ depending on the license type.

#### On-screen Menu Bar Keeps You in Control

Don't lose the crowd—or your cool—in endless menus while you search for content or functions. With the BF1 Series, everything is to hand in a discreet menu bar at the bottom of the screen that offers instant access to source inputs, whiteboard tools, and other controls you use most frequently. Even when the pressure's on, you'll look like a pro.



### Colors Everyone Can See

Color Universal Design (CUD) ensures that colors are reproduced clearly and accurately for the many millions of people living with color-vision defects. The CUD setting is ON/OFF-selectable (default setting is OFF) according to user preference, and the display's power LED indicator color is also CUD-compliant.

#### What is Color Universal Design (CUD)?

Due to genetics or other vision disorders, some people can perceive colors differently. Individuals can have difficulty distinguishing between certain color information is accurately expressed for the comfort and convenience of all.



Note: CUD logo denotes product certification by Color Universal Design Organization in Japan.

#### User-Friendly Menu Bar

Frequently used functions such as input selection, pen tool, enlargement tool, and volume control can be found in the menu bar. Access detailed information or hide it for uninterrupted full-screen display.



Menu fully expanded

#### Quick-Start Whiteboard

Start working on the built-in whiteboard right away just switch on the display. Intuitive operation makes life easy for kids and less tech-savvy presenters.

#### Write and Draw on Video and Still Images

You can write and draw on almost any media you like, including video and still images from external devices. These dynamic multi-media capabilities make it easy for teams to share information, contribute ideas, and solve problems.

Note: Drawing on media transmitted via and Miracast Input is not supported.



Easy to Save and Share

Produce up to 100 pages<sup>\*1</sup> of work on the whiteboard and save them to the built-in memory<sup>#2</sup> or USB thumb drive as JPEG image files. You can also copy data stored on internal memory to a USB drive, or send your pages as image files directly from the screen via email\*3. Keeping everyone in the loop is simple.

\*1 With built-in memory setting to ON. When individual file data size is large, the number of pages that can be saved may decrease. \*2 Built-in memory ON/OFF is included. When OFF is selected, only one whiteboard page can be created. \*3 Can be sent as JPEG format only.



#### Whiteboard Software for PC Extends Your Capabilities

Whiteboard Software for PC offers deeper functionality for power users. As well as adding extra presentation tools and a PowerPoint<sup>®</sup> Link mode for easy import and modification of PowerPoint<sup>®</sup> files, the application's 12-point touch<sup>®1</sup> interface lets a group of people write and draw simultaneously.

\*1 Up to 12-point for Windows<sup>®</sup>, up to 4-point for Mac. Up to 4 points when using the Built-in Whiteboard Software.

More information about whiteboard software: panasonic.net/cns/prodisplays/products/bf1/software.html



### [BF1 Series]

#### Panasonic Wireless Solution

Panasonic's Wireless Display function supports secure high-bandwidth wireless transmission from compatible Windows<sup>+</sup> PCs. Proprietary apps for Windows<sup>+</sup>, Mac, iOS, and Android<sup>™</sup> add a raft of easy-to-use functions, including Multi-Live Mode in split-screen.

#### Wireless Display with Wi-Fi-Certified Miracast\*1

#### Share It On the Big Screen

#### Selectable Display Modes

**Duplicate Mode** 

Mirror vour device's

screen on the display

Smartphone Tablet PC

Still images, video, and audio are all smoothly transmitted peer-to-peer from Windows' PCs and Android' devices. Video content is supported at up to 1080p resolution, with high-bandwidth performance ensuring stutter-free video playback. Display modes comprising Duplicate, Extend, and Second Screen allow your source device screen and the display to interact in different ways depending on your needs in the meeting space or classroom.

Extend Mode

Use the display as an

extended PC screen

PC

Nindows

BF1

Wi Fi

CERTIFIED

Second Screen Only

PC screen is shown only

on the display



Prevents Improper Connection
A PIN code appears when a user attempts to connect to
the display. Only those with access can transmit
wriekessly, preventing improper or accidental use.
and the layer of versalitity and convenience.



\*1 Drawing on media transmitted via Mirroring Input is not supported.

Panasonic Wireless M	lanager
Williuows	Fast and stable wireless connection • Connect 4 or 16 PCs in Multi-Live Mode
Download free from our global web	osite at https://panasonic.net/cns/prodisplays
Quick 3-Step Connection	

 1. Launch App
 2. Select Display
 3. Click to Present

#### Simplified DIGITAL LINK Connection

DIGITAL LINK transmits uncompressed Full HD video, audio, and control commands through a single CAT 5e or higher STP cable for up to 100 m (328 ft). Connect all your source devices to an optional DIGITAL LINK Switcher (ET-YFB200G)/Digital Interface Box (ET-YFB100G) and use just one cable to link your display. This simplifies installation and saves on cabling costs.

Note: Long Reach Mode on ET-YFB200G is not supported.



DVI-D OUT

HDMI 2

VIDEO

Amplifier

DIGITAL LINK 3

#### Other Features

Expand and Customize with SLOT2.0
PJ LINK<sup>™</sup> Compliant
Picture-in-Picture Capability

Built-in Speaker
 Secondary Display
 Protective Glass and AG Screen Surface

000

FT-YFR2000

-

Blu-ray Disc pla

VCR



Selectable 2.4 GHz and 5 GHz\* channels for

areas with Wi-Fi\* congestion are included.


Selectable Channels





VGA 2

Control P



\* This optional product can be purchased in the U.S., Canada, Japan, Australia, and New Zealand.

000



000

DIGITAL LINK 1

(Up to 100 m/328 ft

### BQE1/BFE1 Series

#### Touch-Screen Displays with Easy-to-Use Features for Classrooms & Conference Rooms

In addition to presenting educational materials, these displays can be used as whiteboards\* to improve student understanding. Several students can write on them simultaneously, for active classroom participation.

\*A computer installed with whiteboard software (available free of charge) is required.



#### Whiteboard Software for Full Use of Educational Materials

This software can be used to display educational materials, and to make lessons easier to understand by jotting in notes.

- Presentation Functions\* (Magnifying Glass, Pen/Marker)
- Electronic Pen, Finger-Touch Input
- Screen Capture/Recording Function\*
- Simultaneous Operation of Up to 10 Points\*
- Reading and Writing of JPEG and Other Image Data
   Writing and Saving of PowerPoint<sup>®</sup> Data<sup>\*</sup>

\* For the latest software please visit out global website: panasonic.net/cns/prodisplays/download/software/

#### Large, Easy-to-See Display Sizes for Classrooms and Conference Rooms

A large, 65-inch size that is easy to see in classrooms and conference rooms, and an even larger, 75-inch size are available. Select the one that matches the room size. Terminals for PC and HDMI input support highly detailed Full-HD images of lesson materials and other data. Even complicated drawings and small text are clear and legible as well.



### Touch-Panel Provides Easy-to-Understand Information

Ideal for use as floor maps and signage to describe products in a showroom.

- Multi-touch input allows several people to write simultaneously.
- Easy-to-hear front speaker (included).
- Can be vertically installed. The speaker can also be mounted
- in the vertical configuration.
- Complies with VESA standards. Third-party mounting fixtures can be used.





#### High Visibility for Easy Info Sharing from a Distance

Easy-to-see confirmation of educational materials and data.

 Bright 400-cd/m<sup>2</sup> display of easy-to-see images.
 Anti-glare processing suppresses external reflections for high visibility.

# BQE1/BFE1 Series





Model no.	TH-75BQE1	TH-65BFE1	TH-55LFE8-IR
Screen Size (Diagonal)/Aspect Ratio	75-inch (1892 mm)/16:9	65-inch (1638 mm)	55-inch (1387 mm)/16:9
쉽 Panel Type	VA Panel/E-LED	VA Panel/E-LED	IPS Panel/D-LED
Effective Display Area (W x H)	1650 x 928 mm (65.0" x 36.5") (TBD)	1428 x 803 mm (56.2" x 31.6")	1209 x 680 mm (47.6" x 26.8")
Resolution (H x V)	3840 x 2160	1920 x 1080	1920 x 1080
Brightness (Typ)	400 cd/m <sup>2</sup>	400 cd/m <sup>2</sup>	350 cd/m2
Contrast Ratio	4000:1	4000:1	1200:1
Response Time	8 ms (G to G)	8 ms (G to G)	9 ms (G to G)
Viewing Angle (Horizontal/Vertical)	178°/178° (CR≥10)	178°/178° (CR≥10)	178°/178° (CR≥20)
Vertection Method	Infrared Blocking Detection Method	Infrared Blocking Detection Method	Infrared Blocking Detection Method
Touch Operation	Up to 10-point multi-touch*1	Up to 10-point multi-touch*1	Up to 10-point multi-touch*1
VIDEO In		_	Mini Jack (M3) x 1
HDMI In	HDMI Type A	Connector x 2	_
Component/RGB In	· Dim Open	_	HDMI TYPE-A Connector x 2
DVI-D In	DVI-D 24-ni	n (Digital) x 1	
PC In		e), Plug & Play (VESA DDC 2B)	_
Audio In (L/R)		Jack (M3) x 1	DVI-D 24-pin x 1
Audio Out (L/R)		Jack (M3) x 1	Stereo Mini Jack (M3) x 1 (Shared with PC In)
PC Out		b 15-pin x 1	Mini D-sub 15-pin x 1
		× 1 (For Memory Viewer)	Stereo Mini Jack (M3) x 1 (Shared with DVI-D In)
Serial In		control, RS-232C Compatible	
DIGITAL LINK	D-Sub S-pill X Hor external		TYPE A USB Connector 5V DC/1A (USB 3.0 is not supported.)
LAN			D-sub 9-pin x 1, RS-232C Compatible
Function Slot		_	D-sub y pin x 1, its-252e compatible
Power Requirements	220-240 V AC. 50 Hz/60 Hz		
Power Consumption	370 W	205 W	
Power Off Condition/Stand-by Condition	Approx. 0.5 W/Approx. 0.5 W	Approx. 0 W/Approx. 0.5 W	220-240 V AC, 50 Hz/60 Hz
Dimensions (W x H x D)	1710 x 1072 x 102 mm (67.3" x 42.2" x 4.0")	1490 x 948 x 106 mm (58.7" x 37.4" x 4.2")	175 W
Dimensions (WXTIXD)	(with speaker mounted)	(with speaker mounted)	Approx. 0.3 W
Carton Size (W x H x D)	2010 x 1112 x 250 mm (79.2" x 43.8" x 9.9")	1640 x 1044 x 226 mm (64.6" x 41.2" x 8.9")	Approx. 0.5 W
Weight	2010 x 1112 x 230 1111 (75.2 x 43.0 x 3.3 )	Approx. 44.0 kg (97.0 lbs.)	1293 x 763 x 77 mm (50.9" x 30.0" x 3.0")
weight	Approx. 66.0 kg (145.5 lbs.)	[Approx. 46.0 kg (101.4 lbs.) with speaker mounted]	1365 x 864 x 185 mm (53.7" x 34.0" x 7.3")
☐ Gross Weight	Approx. 81.0 kg (178.6 lbs.)	Approx. 57.0 kg (125.7 lbs.)	Approx. 35.5 kg (78.3 lbs.)
Pitch for Wall-Hanging	VESA Compliant 400 x 400 mm (15.8" x 15.8")	VESA Compliant 400x 400 mm (15.8" x 15.8")	Approx. 44.0 kg (97.0 lbs.)
Protective Glass Thickness	Approx. 4 mm (0.16")	Approx. 4 mm (0.16")	VESA Compliant 400 x 400 mm (15.8" x 15.8")
Built-in Speaker	—	—	Approx. 4 mm (0.16")
External Speaker	20 W [10 W + 10 W] (10 % THD), W764 x H82 x D59 mm (W30.1" x H3.3" x D2.3")	16 W [8 W + 8 W], W764 x H82 x D59 mm (W30.1" x H3.3" x D2.3")	20 W [10W + 10 W] (10% THD) —
Orientation	Landscape/Portrait	Landscape/Portrait	Landscape/Portrait
Tilting Angle	TBD	Up to 20 degrees backward in landscape orientation	0-20 degrees forward with landscape setting
Operating Environment	Temperature: 0 °C to 40 °C (32 °F to 104 °F) [for up to	1400 m (4593 ft) altitude] / 0 °C to 35 °C (32 °F to 95 °F)	Temperature: 0 °C to 40 °C (32 °F to 104 °F)
s provide second		altitude], Humidity: 20 % to 80 % (Non-condensation)	Humidity: 20 % to 80 % (Non Condensation)
Storage Environment		, Humidity: 20 % to 80 % (Non-condensation)	Temperature: -20 °C to 60 °C (-4 °F to 140 °F) / Humidity: 20 % to 80 % (Non Conden
Operating Time*2	•	/day	16 h/day
Pedestal	TY-ST55PE9	TY-ST55PE9	TY-ST55PE9
Mobile Stand	_	_	ET-SWA100 Series
S Wall-hanging Bracket	_	_	_
Ceiling-hanging Bracket	_	_	-
Easy Wireless Stick	_	_	_
O Digital Interface Box	_	_	_
DIGITAL LINK Switcher	_	_	
Early Warning Software	_	_	_
Lany Warning Software			

65"

\*1: When using the Whiteboard Software for Windows<sup>\*</sup>. Up to 4-point using the Whiteboard Software for Mac. \*2: In case running for a long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain on the screen. However, image retention can gradually disappear by displaying a moving images.





55"



owsense			
Model no.	TH-55AF1-SST	TH-49AF1-SST	TH-42AF1-SST
Screen Size (Diagonal)/Aspect Ratio	55-inch (1387 mm)/16:9	49-inch (1232 mm)/16:9	42-inch (1064 mm)/16:9
Panel Type	IPS Panel/E-LED	IPS Panel/E-LED	IPS Panel/E-LED
Effective Display Area (W x H)	1209 x 680 mm (47.6" x 26.7")	1073 x 604 mm (42.2" x 23.7")	927 x 521 mm (36.5" x 20.5")
Resolution (H x V)	1920 x 1080	1920 x 1080	1920 x 1080
Brightness (Typ)	500 cd/m <sup>2</sup>	500 cd/m <sup>2</sup>	500 cd/m <sup>2</sup>
Contrast Ratio	1300:1	1300:1	1300:1
Dynamic Contrast Ratio	50000:1	50000:1	50000:1
Response Time	8 ms (G to G)	8 ms (G to G)	8 ms (G to G)
Viewing Angle (Horizontal/Vertical)	178°/178° (CR≥10)	178°/178° (CR≥10)	178°/178° (CR≥10)
Panel Surface Treatment	Anti-Glare (Haze 10 %)	Anti-Glare (Haze 10 %)	Anti-Glare (Haze 10 %)
OS		id 4.4.3	Android 4.4.3
CPU		0 GHz (Quad)	Cortex-A9, 1.0 GHz (Quad)
Memory		/ ROM 8 GB	RAM 1 GB / ROM 8 GB
VIDEO In	BNC x 1 (Shared w	vith Component In)	BNC x 1 (Shared with Component In)
Audio In (L/R)	Stereo Mini Jack (M3) x 1 (	Shared with Component In)	Stereo Mini Jack (M3) x 1 (Shared with Component In)
HDMI In	HDMI Type A	Connector x 2	HDMI Type A Connector x 2
Component/RGB In	BNC x 1 set (Sha	red with VIDEO In)	BNC x 1 set (Shared with VIDEO In)
Audio In (L/R)	Stereo Mini Jack (M3) x	1 (Shared with Video In)	Stereo Mini Jack (M3) x 1 (Shared with Video In)
DVI-D In		4-pin x 1	DVI-D 24-pin x 1
Audio In (L/R)		x 1 (Shared with PC In)	Stereo Mini Jack (M3) x 1 (Shared with PC In)
DVI-D Out		4-pin x 1	DVI-D 24-pin x 1
PC In		pin x1 (Female)	Mini D-Sub 15-pin x1 (Female)
Audio In (L/R)		1 (Shared with DVI-D In)	Stereo Mini Jack (M3) x 1 (Shared with DVI-D In)
Audio Out (L/R)		Jack (M3) x 1	Stereo Mini Jack (M3) x 1
Serial In/Out		RS-232C Compatible	D-sub 9-pin x 1/x 1, RS-232C Compatible
USB		5 V/1 A (USB3.0 is not supported)	USB connector (TYPE A) x 1, DC 5 V/1 A (USB3.0 is not supported
IR In/Out		ck (M3) x 1 / x 1	Stereo Mini Jack (M3) x 1 / x 1
LAN		DBASE-TX/1000BASE-T, Compatible with PJLink™	RJ45 x 1 for Network Connection, 10BASE-T/100BASE-TX/1000BASE-T, Compatible with PJLi
USB		E A) x 3, DC 5 V/500 mA	USB2.0 connector (TYPE A) x 3, DC 5 V/500 mA
Micro-USB		Connector x 1	Micro USB Connector x 1
microSD card slot	microSD, m	icroSDHC x 1	microSD, microSDHC x 1
😚 Wireless LAN	IEEE 802.	11a/b/g/n	IEEE 802.11a/b/g/n
Power Requirements	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz
Power Consumption	196 W	181 W	160 W
Power Off Condition	Approx. 0.3 W	Approx. 0.3 W	Approx. 0.3 W
Stand-by Condition		, LATFORM standby] is set to [Off]) PLATFORM standby] is set to [On])	Approx. 0.5 W (When [OpenPort PLATFORM standby] is set to [C Approx. 20 W (When [OpenPort PLATFORM standby] is set to [C
Dimensions (W x H x D)	1309 x 784 x 76mm (51,5" x 30,9" x 3,0")	1171 x 701 x 76mm (46,1" x 27,6" x 3,0")	947 x 541 x 76mm (37,3" x 21,3" x 3,0")
Carton Size (W x H x D)	1444 x 922 x 223 mm (56.9" x 36.3" x 8.8")	1308 x 846 x 203 mm (51.5" x 33.4" x 8.0")	1123 x 743 x 203 mm (44.3" x 29.3" x 8.0")
Bezel Width	48mm (1,89")	48mm (1,89")	48mm (1,89")
Weight	49kg (108 lbs.)	39.8kg (87,7 lbs.)	33.5kg (73,85 lbs.)
Gross Weight	57kg (125,6 lbs.)	46.5kg (102,5 lbs.)	38.5kg (84,9 lbs.)
Pitch for Wall-Hanging	VESA Compliant 400x 400 mm (15.8" x 15.8")	VESA Compliant 400x 400 mm (15.8" x 15.8")	VESA Compliant 200 x 200 mm (7.9" x 7.9")
Built-in Speakers	-		
	20 W [10 W + 10 W]	20 W [10 W + 10 W]	20 W [10 W + 10 W]
Orientation		nt 0-45 degrees for both left and right)	Landscape/Portrait (Angle adjustment 0-45 degrees for both left and r
Tilting Angle*1	0-45 degrees forward/backward (Angle adjustment is not possible for	with landscape/portrait setting*1 forward/backward tilting installation.)	0-45 degrees forward/backward with landscape/portrait setting* (Angle adjustment is not possible for forward/backward tilting installat
Operating Environment	Temperature: 0 °C to 40 °C (32 °F to 10 Humidity: 20 % to 80	4 °F)*² : 0 °C to 35 °C (32 °F to 95 °F)* <sup>3</sup> / % (Non-condensation)	Temperature: 0 °C to 40 °C (32 °F to 104 °F)* <sup>2</sup> : 0 °C to 35 °C (32 °F to 95 °F)' Humidity: 20 % to 80 % (Non-condensation)
Storage Environment	Temperature: -20 °C to 60 °C (-4 °F to 140 °F).	/ Humidity: 20 % to 80 % (Non Condensation)	Temperature: -20 °C to 60 °C (-4 °F to 140 °F) / Humidity: 20 % to 80 % (Non Condensat
Operating Time <sup>*4</sup>		/day	24 h/day
Pedestal	TY-ST55PE9	TY-ST55PE9	TY-ST55PE9
Early Warning Software*5	ET-SWA100 Series	ET-SWA100 Series	ET-SWA100 Series
Auto Display Adjustment Upgrade Kit*6	TY-VUK10	TY-VUK10	TY-VUK10
Multi Window Processor*7	ET-MWP100G	ET-MWP100G	ET-MWP100G
Detection Method		nse™ Touch	ShadowSense™ Touch
Touch Operation	Multi-touch u	ip to 10 points	Multi-touch up to 10 points
Protective Glass Thickness		ed safety glass	4mm hardened safety glass

#### Featuring ShadowSense<sup>™</sup> touch technology



#### **ShadowSense**

ShadowSense<sup>™</sup> touch is based upon the precise and accurate detection of an object's shadow as it enters, hovers within, or transitions out of a sensor's field of view.

High durability and touch accuracy - Works even in very bright environments - Works with any input device (fingers, gloves, pens) - Avoids accidental touches by recognizing pens, fingers, sleeves or objects used as an eraser - High touch accuracy and fast response - Very robust due to high tolerance towards dirt and objects blocking sensors - Protection glass: 4mm hardened safety glass, smooth anti-glare surface for easy drawing and writing.

\*1: Please contact your sales representative with regard to the tilt angle before installation. \*2: for up to 1400 m (4593 ft) altitude \*3: for between 1400 m (4593 ft) and 2800 m (9186 ft) altitude. Depending on the temperature or humidity conditions, uneven brightness may be observed. This is not a malfunction. This unevenness will disappear while applying current continuously. If not, consult the distributor. \*4: In case of long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain on the screen. However, image retention can gradually disappear by displaying a moving images. \*5: Suffix of the part number may differ depending on the license type. \*6: Download the latest Video Wall Manager from PASS in advance. (https://panasonic.net/cns/prodisplas/pass/) \*7: The availability varies depending on the country.

## LF80-SST Series

D



55"



Model no.	TH-55LF80-SST	TH-49LF80-SST	TH-42LF80-SST
Screen Size (Diagonal)/Aspect Ratio	55-inch (1387 mm)/16:9	49-inch (1232 mm)/16:9	42-inch (1064 mm)/16:9
Panel Type	IPS Panel/E-LED	IPS Panel/E-LED	IPS Panel/E-LED
Effective Display Area (W x H)	1209 x 680 mm (47.6" x 26.7")	1073 x 604 mm (42.2" x 23.7")	927 x 521 mm (36.5" x 20.5")
Resolution (H x V)	1920 x 1080	1920 x 1080	1920 x 1080
Brightness (Typ)	500 cd/m <sup>2</sup>	500 cd/m <sup>2</sup>	500 cd/m <sup>2</sup>
Contrast Ratio	1300:1	1300:1	1300:1
Dynamic Contrast Ratio	50000:1	50000:1	50000:1
Response Time	8 ms (G to G)	8 ms (G to G)	8 ms (G to G)
Viewing Angle (Horizontal/Vertical)	178°/178° (CR≥10)	178°/178° (CR≥10)	178°/178° (CR≥10)
Panel Surface Treatment	Anti-Glare (Haze 10 %)	Anti-Glare (Haze 10 %)	Anti-Glare (Haze 10 %)
Detection Method		nse™ Touch	ShadowSense <sup>TM</sup> Touch
Touch Operation		ip to 10 points	Multi-touch up to 10 points
Protective Glass Thickness		ed safety glass	4mm hardened safety glass
VIDEO In			· · ·
		Component /RGB Y/G)	BNC x 1 (Shared with Component /RGB Y/G)
Audio In (L/R)		Shared with Component In)	Stereo Mini Jack (M3) x 1 (Shared with Component In)
HDMI In		Connector x 2	HDMI Type A Connector x 2
Component/RGB In		red with Video In)	BNC x 1 set (Shared with Video In)
Audio In (L/R)		1 (Shared with Video In)	Stereo Mini Jack (M3) x 1 (Shared with Video In)
DVI-D In		4-pin x 1	DVI-D 24-pin x 1
Audio In (L/R)		x 1 (Shared with PC In)	Stereo Mini Jack (M3) x 1 (Shared with PC In)
DVI-D Out		4-pin x 1	DVI-D 24-pin x 1
PC In		pin x 1 (Female)	Mini D-Sub 15-pin x 1 (Female)
Audio In (L/R)	Stereo Mini Jack (M3) x	1 (Shared with DVI-D In)	Stereo Mini Jack (M3) x 1 (Shared with DVI-D In)
Audio Out (L/R)	Stereo Mini	Jack (M3) x 1	Stereo Mini Jack (M3) x 1
Serial In/Out	D-sub 9-pin x 1/x 1,	RS-232C Compatible	D-sub 9-pin x 1/x 1, RS-232C Compatible
DIGITAL LINK	RJ45 x 1 100BASE-TX, Compatibl	e with PJLink™ (Shared with LAN)	RJ45 x 1 100BASE-TX, Compatible with PJLink™ (Shared with LAN
LAN	RJ45 x 1 100BASE-TX, Compatible wit	th PJLink™ (Shared with DIGITAL LINK)	RJ45 x 1 100BASE-TX, Compatible with PJLink™ (Shared with DIGITAL LINK)
IR In/Out	Stereo Mini Ja	ck (M3) x 1 / x 1	Stereo Mini Jack (M3) x 1 / x 1
USB	USB Type A Connector x 1, DC 5	V/1A (USB 3.0 is not supported.)	USB Type A Connector x 1, DC 5V/1A (USB 3.0 is not supported.)
Function Slot	-	_	-
Power Requirements	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz	220-240 V AC, 50 Hz/60 Hz
Power Consumption	196 W	181 W	160 W
Power Off Condition	Approx. 0.3 W	Approx. 0.3 W	Approx. 0.3 W
Stand-by Condition	Approx. 0.5 W (When [OpenPort I	PLATFORM standby] is set to [Off])	Approx. 0.5 W (When [OpenPort PLATFORM standby] is set to [Off]
	Approx. 20 W (When [OpenPort F	PLATFORM standby] is set to [On])	Approx. 20 W (When [OpenPort PLATFORM standby] is set to [On]
Dimensions (W x H x D)	1309 x 784 x 76mm (51,5" x 30,9" x 3,0")	1171 x 701 x 76mm (46,1" x 27,6" x 3,0")	947 x 541 x 76mm (37,3" x 21,3" x 3,0")
Carton Size (W x H x D)	1444 x 922 x 223 mm (56.9" x 36.3" x 8.8")	1308 x 846 x 203 mm (51.5" x 33.4" x 8.0")	1123 x 743 x 203 mm (44.3" x 29.3" x 8.0")
Bezel Width	48mm (1,89")	48mm (1,89")	48mm (1,89")
Weight	49kg (108 lbs.)	39.8kg (87,7 lbs.)	33.5kg (73,85 lbs.)
Gross Weight	57kg (125,6 lbs.)	46.5kg (102,5 lbs.)	38.5kg (84,9 lbs.)
Pitch for Wall-Hanging	VESA Compliant 400x 400 mm (15.8" x 15.8")	VESA Compliant 400x 400 mm (15.8" x 15.8")	VESA Compliant 200 x 200 mm (7.9" x 7.9")
Built-in Speakers	20 W [10 W + 10 W]	20 W [10 W + 10 W]	20 W [10 W + 10 W]
Orientation		nt 0-45 degrees for both left and right)	Landscape/Portrait (Angle adjustment 0-45 degrees for both left and righ
Tilting Angle*1		with landscape/portrait setting*1	0-45 degrees forward/backward with landscape/portrait setting*1
	(Angle adjustment is not possible for		(Angle adjustment is not possible for forward/backward tilting installation
Operating Environment	Temperature: 0 °C to 40 °C (32 °E to 10	4 °F)*2 : 0 °C to 35 °C (32 °F to 95 °F)*3 /	Temperature: 0 °C to 40 °C (32 °F to 104 °F)*2 : 0 °C to 35 °C (32 °F to 95 °F)*3 /
		% (Non-condensation)	Humidity: 20 % to 80 % (Non-condensation)
Storage Environment	-	/ Humidity: 20 % to 80 % (Non Condensation)	Temperature: -20 °C to 60 °C (-4 °F to 140 °F) / Humidity: 20 % to 80 % (Non Condensation
Operating Time*4		/day	24 h/day
Pedestal	TY-ST55PE9	TY-ST55PE9	TY-ST55PE9
Wall-hanging Bracket	_	_	
Digital Interface Box	ET-YFB100G	ET-YFB100G	ET-YFB100G
DIGITAL LINK Switcher	ET-YFB200G	ET-YFB200G	ET-YFB200G
Early Warning Software*6	ET-SWA100 Series	ET-SWA100 Series	ET-SWA100
Auto Display Adjustment Upgrade Kit*7	TY-VUK10	TY-VUK10	TY-VUK10
Multi Window Processor*8	ET-MWP100G	ET-MWP100G	ET-MWP100G
Multi Window Processor's	ET-WWYP100G	ET-WWPTUUG	EI-MWP100G

#### Featuring ShadowSense™ touch technology



#### **ShadowSense**

ShadowSense<sup>™</sup> touch is based upon the precise and accurate detection of an object's shadow as it enters, hovers within, or transitions out of a sensor's field of view.

High durability and touch accuracy - Works even in very bright environments - Works with any input device (fingers, gloves, pens) - Avoids accidental touches by recognizing pens, fingers, sleeves or objects used as an eraser - High touch accuracy and fast response - Very robust due to high tolerance towards dirt and objects blocking sensors - Protection glass: 4mm hardened safety glass, smooth anti-glare surface for easy drawing and writing.

\*1: Please contact your sales representative with regard to the tilt angle before installation. \*2: for up to 1400 m (4593 ft) altitude \*3: for between 1400 m (4593 ft) and 2800 m (9186 ft) altitude. Depending on the temperature or humidity conditions, uneven brightness may be observed. This is not a malfunction. This unevenness will disappear while applying current continuously. If not, consult the distributor.

\*4: In case of long time, the moving image is recommended to be displayed. If you display a still picture for an extended period, the image retention might remain on the screen. However, image retention can gradually disappear by displaying a moving image. \*5: Suffix of the part number may differ depending on the license type. \*6: Download the latest Video Vall Manager from PASS in advance, (https://panasonic.net/cns/prodisplas/pass) \*7: The availability varies depending on the country.

### Panasonic Software Line-up

In order to maximize the use of professional displays, Panasonic offers a variety of software and applications (some free of charge, and others for a fee).

#### Downloadable for Free

#### Multi Monitoring & Control Software

This free Panasonic software enables you to monitor and control up to 2048 devices over a LAN network from a single PC. As a monitoring function, the status of multiple devices can be listed in groups, and then detailed information on each device can be separately displayed. As a control function, control commands such as power ON/OFF, input switching and command inputs can be executed, and a schedule function can be used. For models that support the USB Media Player, this software can also be used to rewrite the content in the USB memory device.



Compatible Displays: VF1H, LFV70, LFV60, LFV6, AF1 Series, SF1H Series, LF80 Series, SF2 Series, LF8 Series, BF1 Series, LFE8 Series panasonic.net/cns/prodisplays/download/software/#monitoring

#### Content Management Software 🛛 🛛 🕊 🖳

Content Management Software makes it possible to create scheduling data and media playlist on a PC and save it to one or more SD Cards. Insert the card into Space Players to execute the schedule. The software reduces complexity for temporary installations or where the device is frequently moved from place to place.



USB media

oSD/ 3. Insert device into display to execute schedule

#### Compatible Display: AF1 Series, SF2 Series panasonic.net/cns/prodisplays/download/software/

#### Whiteboard Software

This simple software is easy to operate. Requiring no PC installation, it can be started and used from external memory. Switching to a convenient, simple menu when using the Remote Pointer is also supported.



Compatible Displays: BF1 Series, BQE1 Series panasonic.net/cns/prodisplays/download/software/#whiteboard

Windows

#### Wireless Manager

This application supports wired or wireless connection of screen display images from a PC to the display. Be sure to uninstall the old version of the software before upgrading to the new version.



Compatible Displays: BF1 Series

panasonic.net/cns/prodisplays/download/software/#wireless

#### Optional

#### Early Warning Software (ET-SWA100 Series\*)

Early Warning Software monitors the status of displays and projectors connected to an intranet and informs you when an abnormality is detected or predicted, and when there are symptoms of trouble. This minimizes downtime to provide more stable operation.

\* Part number suffix may differ depending on the license type.



#### Video wall Manager (download for free) and Auto Display Adjustment Upgrade Kit (TY-VUK10)

Panasonic's free Video Wall Manager software can be used with LCD Video Wall Series displays. With this software, you can calibrate display color using a color sensor, adjust display settings, and control and manage data via PC. If software is upgraded with an optional TY-VUK10 Auto Display Adjustment Upgrade Kit, brightness and color among multiple displays can be automatically calibrated using a compatible camera (Nikon D5200/D5300/D5500)\*.





\* Available only with normal zoom lens: AF-S DX NIKKOR 18-55 mm f/3.5-5.66 VR, AF-S DX NIKKOR 18-140 mm f/3.5-5.66 ED VR, AF-S DX NIKKOR 18-55 mm f/3.5-5.66 VR II

For more information, please visit the PASS: panasonic.net/cns/prodisplays/pass/

#### Mobile App (iOS/Android)

#### Wireless Projector

This is an application that lets you send displayed screenshot, document files (PDF, PowerPoint, Excel, Word), and JPEG/PNG images saved to Android devices (tablets and smartphones) to a Panasonic wireless display over a wireless LAN (Wi-Fi), and display them. The application also lets you rotate the screen, enlarge or reduce the screen with a pinch operation, and flip through pages with a flick operation.



Dedicated wireless apps for iOS and Android™
 Fewer steps to connect
 Wide media compatibility and functionality

For more information, please visit the Global Website: panasonic.net/cns/prodisplays/download/software/#wireless



			4k									Indo	or								1	Stan	dard					Vid	eo Wa	u		ntera ollabo			Int	terac	tive :	Signag	e	Ou	door
<b>O</b> ptional <b>A</b> ccess	ories	TH-98LQ70 TH-98LQ70	TH-84LQ70 TH-84LQ70	TH-55AF1	TH-49AF1	TH-42AF1	TH-805F2H TH-705F2H	TH-55SF1H	TH-49SF1H	TH-42SF1H	TH-55LF80	TH-49LF80	TH-42LF80	TH-65SF2	TH-55SF2	TH-495F2		TH-43SF2	TH-84EF1	TH-75EF1	ТН-65ЕF1 ти 22EE1		TH-55LFE8 TH-48LFE8	TH-43LFE8	TH-84EF1-MRS	TH-75EF1-MRS	TH-55VF1H	TH-55LFV70	TH-55LFV6	TH-55LFV8 TH-49LFV8	TH-80BF1	TH-65BF1	TH-75BQE1	TH-65BFE1	TH-55AF1-SST ти-79AE1-сст	1H-49AF1-551 TH-49AE1-551		TH-49LF80-SST	TH-42LF80-SST	TH-47LFX60	TH-47LFX6N
Screen Size (inch)		98	84	55	49	42 8	30 70	1 55	49	42	55	49	42	65	55	49		43	84	75 (	65 3	2 5	5 48	43	84	75	55	55	55	55 49	80	65	75	65	55 4	9 4	2 5	5 49	42	47	47
ខ្ទ័ <sub>ម</sub> DVI-D	TY-FB11DD	-	-	-	-	-			-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		Yes	Yes	-	-		-   -		-	-	-	-
3G-SDI Terminal Board	TY-TBN03G	Yes	Yes	-	-	- Y	es Ye	s -	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		-	-	-	-		-   -		-	-	-	-
Pedestal	TY-ST103PF9	Yes		-	-	-		-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		-	Yes	-	-				-	-	-	-
	TY-ST85P12	-	Yes	-	-	-	-   -	-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		-	-	-	-		-   -	-   -	-	-	-	-
	TY-ST75PE9	-	-	-	-	- Y	es Ye	s -	-	-	-	-	-	-	-	-		-	-	-	-   -	-		-	-	-	-	-	-		-	-	Yes	Yes		-   -	-   -	-	-	-	-
	TY-ST65P20*1	-	-	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		Yes	-	-	-		-   -		-	· ·	-	-
	TY-ST55PE9	-	-	-	-	-	-   -	-	-	-	-	-	-	Yes	Yes	-		-	-	-	-   -			-	-	-	-	-	-		-	-	-	- 1	Yes Ye	es   Ye	es Ye	es Yes	Yes	-	-
	TY-ST42P50	-	-	-	-	-	-   -	-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		-	Yes	-	-		-   -			-	-	-
	TY-ST43PE9	-	-	-	-	-	-   -	-	-	-	-	-	-	-	-	Yes		Yes	-	-	-   -	•		-	-	-	-	-	-		-	-	-	-		-   -			-	-	-
	TY-ST43PE8	-	-	Yes	Yes	Yes		Yes	Yes	Yes	Yes	Yes	Yes	-	-	-		-	-	-			es Yes	Yes	-	-	-	-	-		-	-	-	-		-   -		-	· ·	-	-
	TY-ST32PE1	-	-	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-		es		-	-	-	-	-	-		-	-	-	-					<u> </u>		-
Mobile stand	TY-ST85PB1*1	-	Yes	-	-	-	-   -	-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		-	-	-	-		-   -			-	-	-
	TY-ST80LF70*1	-	-	-	-	-	-   -	-	-	-	-	-	-	-	-	-		-	-	-	-   -			-	-	-	-	-	-		Yes	-	-	-		-   -			-	-	-
	TY-ST65PB2*1	-	-	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		-	-	-	-					-	-	-
	TY-ST50PB2*1	-	-	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-		•		-	-	-	-	-	-		-	-	-	-					<u> </u>	-	
2 Wall-hanging Bracket	TY-WK103PV9*1	Yes	-	-	-	-	-   -	-	-	-	-	-	-	-	-	-		-	-	-		•		-	-	-	-	-	-		-	Yes	-	-		-   -				-	-
Mall-hanging Bracket (angled)	TY-WK42PV20 TY-WK65PR20*1	-	-	-	-	-		-	-	-	-	-	-	-		-		-	-	-	_			-	-	-	-	-	-		-	-	-	-+					<u> </u>	-	-
Wall-hanging Bracket (angled)	TY-WK42PR20	-	-	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		-	-	-	-				-	-	-	-
≥ Ceiling-hanging Bracket	TY-CE103PS10*1	- Yes*3	-	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		-	- Yes*2	-	-+-				<u> </u>	<u> </u>	-	-
Centing-nanging Bracket	TY-CE85PS12*1	-	Yes*3	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		-	-	-	-					-	-	-
	TY-CE42PS20*1	-	Tes	-	-	-			-	-	-	-		-	-	-		-	-	-					-	-	-	-	-		-	-	-								
Installation Mount	TY-VK55LV1	-	-	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-					-	-	Yes 1	Yes	Yes	Yes -		-	-	-					+-	-	-
(Landscape setting only)	TY-VK49LV2	-	-		-		-   -		-		-				-				-									-	-	- Yes										-	
(Euliuscupe setting only)	TY-VK47LV1	-	-	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-			-	-	-							-
Remote Control Kit	TY-RM50VW	-	-	- 1	-	-		-	-	-	-	-	-	-	-	-		-	-	-				· ·	-	-	-	- 1	-		· ·	-	- 1	- 1					<u> </u>	1 -	-
Cover Frame Kit for 55"	TY-CF55VW1	-	-	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	Yes	-	-		-	-	-	- 1		-   -			-	-	-
Cover Frame Kit for 55"	TY-CF55VW50	-	-	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-				-	-	-		Yes		Yes Yes	-	-	-	- 1		-   -			- I	-	-
Cover Frame Kit for 47"	TY-CF47VW5*1	-	-	-	-	-	-   -	-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		-	-	-	- 1		-   -		1	-	-	-
DIGITAL LINK Switcher	ET-YFB200G	Yes	Yes	- 1	-	- Y	es Ye	s Yes	Yes	Yes	Yes*4	Yes*4	Yes*4	-	-	-	1	-	-	-				-	-	-	Yes 1	Yes	-		Yes*5	-	- 1	-		-   -	- Yes	s*4 Yes*	4 Yes*4	4 -	- 1
Digital Interface Box	ET-YFB100G	Yes	Yes	-	-	- Y	es Ye	s Yes	Yes	Yes	Yes*4	Yes*4	Yes*4	-	-	-		-	-	-				-	-	-	Yes	Yes	-		Yes	-	-	- 1		-   -	- Yes	s*4 Yes*4	4 Yes*	4 -	-
Easy Wireless Stick	ET-UW100*6	-	-	-	-	-	-   -	-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		Yes	Yes*5	-	-		-   -		-	-	-	-
Multi Window Processor	ET-MWP100*7	Yes	Yes	Yes	Yes	Yes Y	es Ye	s Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes		Yes	Yes Y	res Y	'es Ye	s Y	es Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes Yes		Yes	-	- 1	Yes Ye	es Ye	es Ye	s Yes	Yes	Yes	Yes
Whiteboard Software for PC*8		-	-	-	-	-		-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		Yes	Yes	Yes	Yes				-	-	-	-
w Wireless Manager		-	-	-	-	-	-   -	-	-	-	-	-	-	-	-	-		-	-	-				-	-	-	-	-	-		Yes	Yes	-	-		-   -	-   -	-	-	-	-
Multi Monitoring & Control Software*8		-	-	Yes	Yes		es Ye			Yes	Yes	Yes	Yes	Yes	Yes	Yes		Yes	Yes Y	íes   Y	'es Ye	s Y	es Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes Yes	Yes	Yes	-			es Ye					-
Content Management Software		-	-	Yes	Yes		es Ye			-	-	-	-	Yes	Yes	Yes		Yes	-	-				-	-	-		-	-		-	Yes	-			es Ye			-	-	-
Video Wall Manager		-	-	Yes	Yes		es Ye				Yes	Yes		Yes	Yes	Yes		Yes	Yes Y	íes Y	'es Ye	s	-   -	-	Yes	Yes		Yes	Yes	Yes Yes	-	Yes	-			es Ye	es Ye				-
Auto Display Adjustment Upgrade Kit	TY-VUK10*	-		Yes	Yes		es Ye			Yes		Yes		Yes	Yes	Yes		Yes	-	-				-	-	-	Yes \	Yes	Yes	Yes Yes	-	-	-	- /	Yes Ye	es Ye					-
Early Warning Software	ET-SWA100 <sup>+10</sup>	Yes	Yes	Yes	Yes	Yes Y	es Ye	s Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes		Yes	Yes Y	fes   Y	'es Ye	es Y	es Yes	Yes	Yes	Yes	Yes \	Yes	Yes	Yes Yes	Yes	-	Yes	Yes	Yes Ye	es Ye	es Ye	es Yes	Yes	Yes	Yes

The specifications has a case to change without notice.

\*1: Production discontinued. Please contact the sales company for options regarding discontinued products. \*2: The Wall-hanging Bracket (TY-WK65PR20) suitable for both angled and vertical use. Also usable for portrait mounting in 0 degree. For vertical use only when using the TH-65BF1.

\*3: Tilt angle limited to 10 degree maximum. \*4: TH-55/49/42 LF80 only. \*5: Long Reach Mode on ET-YFB200G is not supported.
 \*6: The product can be purchased in the US., Canada, Japan, Australia, and New Zealand. \*7: The availability varies depending on the country.
 \*8: Downloadable free. For more information, please visit Global website. https://panasonic.net/cns/prodispays/downoad/software/

\*9: Download the latest Video Wall Manager from PASS in advance. https://panasonic.net/cns/prodisplays/pass/

\*10: Part number suffix may differ depending on the license type.

	4	4k								In	door									Sta	andar	d				Video	Wall			nteractiv ollaborat			Ir	iterac	tive S	ignag	je	Outd	loor
Features	TH-98LQ70 TH-98LQ70L	TH-84LQ70 TH-84LQ70	TH-55AF1	TH-49AF1	TH-42AF1	TH-80SF2H	TH-70SF2H TH-55SF1H	TH-49SF1H	TH-42SF1H	TH-55LF80	TH-49LF80	TH-42LF80	TH-655F2	TH-555F2	TH-49SF2	TH-43SF2	TH-84EF1	TH-75EF1	TH-65EF1	TH-32EF1	TH-55LFE8	TH-48LFE8	TH-43LFE8 TH-84EF1-MRS	TH-75EF1-MRS	TH-55VF1H	TH-55LFV70 TH-55LFV6	TH-55LFV8	TH-49LFV8	TH-80BF1	TH-65BF1 TH-75BQE1		TH-55LFE8-IR	TH-55AF1-SST	TH-49AF1-SST	TH-42AF1-55T TH-661 680-66T	TH-491 F80-531	TH-42LF80-SST	TH-47LFX60	TH-47LFX6N
Screen Size (inch) LinkRay Compatible	98 -	- 84	55 -	49 -		80 Yes	70 55 Yes Yes	49 Yes	42 Yes	55 -	49 -	42 E	55 5 -	-	49 -	43 -	84 -	75 -	65 -	32	55 -	48 -	43 84	75 -	55 -	55 55	55	49 -	80	65 75	65 -	65 -	-	49 4 -	42 5 	5 49	42	47	47 -
OpenPort PLATFORM®	-	-	Yes	Yes	Yes	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-		-	-	-		-	-			es -		-	-	-
2 Touch Operation	-	-	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-		-	-	Yes	Yes Yes	Yes	Yes	Yes \	íes Y	es Ye	es Ye	s Yes		-
은 IP Rating	-	-	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-		-	-	-		-	-	-	-			-		IP55
S Operating Time	24	24	24	24			24 24		24	24					24	24	16	16	16	16	16	16	16 16	16	24	24 24	24	24	18	18 16	16	16	24	24 2		4 24			24
E DIGITAL LINK	Yes	Yes	-	-			Yes Yes		Yes					_	/es*2	Yes*2	-	-	-	-	-	-		-	Yes	Yes -	-	-	Yes	Yes -	-	-	-	-	- Ye	s*1 Yes	*1 Yes*1		Yes
Wireless Function	-	-	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-		-	-	Yes	Yes -	-	-	-	-		-	-	-	-
ග Protective Glass	Yes*3	Yes*3	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-		-	-	Yes	Yes Yes	Yes	Yes	Yes \	íes   Y	es Ye	s Ye	s Yes		Yes
Function Slot		TNX	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-		-	-	SLO	T 2.0 -	-	-	-	-			-	-	-
4 input Multi Display (up to FHD)	Yes	Yes	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-		-	-	-		-	-	-	-			-	-	-
S Outdoor Installation	-	-	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-		-	-	-		-	-	-	-		-	-		Yes
Portrait	Yes	Yes	Yes	Yes			Yes Yes		Yes						Yes	Yes	Yes	-		Yes		Yes	Yes Yes	-	Yes	Yes Yes		Yes		Yes Yes	Yes					s Ye			Yes
Hulti Screen (Multi Display settings)	-	-	Yes	Yes	Yes	Yes	Yes Yes	Yes	Yes	Yes	Yes \	/es Y	es Y	es	Yes		Yes	Yes	Yes	Yes	Yes	Yes	Yes Yes	Yes	Yes	Yes Yes		Yes	-		-	-	Yes \	íes Y	es Ye	es Ye	s Yes	Yes	Yes
Pre Calibration	-	-	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-	Yes	Yes Yes	Yes	Yes	-		-	-	-	-		-	-	-	-
Ean-less Design	-	-	Yes	Yes	Yes	Yes	Yes Yes	Yes	Yes	Yes	Yes	íes Y	es Y	es	Yes	Yes	Yes Yes	Yes	Yes	Yes -	-	-	-		Yes	Yes	Yes \	/es Y	'es Ye	es Ye	s Yes	-	-						
Built-in Whiteboard	-	-	-	-	-	-		-	-	-	-	-	-	-	-	- Yes		- */	-	-	-	-		-	-		-	-	Yes	Yes -	-	-	-	-		· -	-	-	-
USB Media Player			Yes	Yes			Yes Yes		Yes						Yes					Yes*4		Yes*4			Yes	Yes Yes		-	-		-	-				s Ye			-
Data Cloning (Using by USB memory)	-	-	Yes -	Yes			Yes Yes		Yes	Yes					Yes	Yes	Yes	Yes	Yes -	Yes			Yes Yes	Yes	Yes	- Yes		-	-		-	-	Yes \	res Y	es Ye	es Ye	s Yes		-
Data Cloning (via LAN) HDMI CEC	-	-	-	-			Yes -	-	-	-					Yes	Yes	_	-	-	-	-	-		-	Yes		-	-	-		-	-	-	-		-	-	-	-
	_	-	-	-			Yes -	-	-	-	-				Yes	Yes	-	-	-	-	-	-	- Yes	-	-		-	-	-		-	-	-	-	-   -	-	-	-	-
Startup Image Settings Color Matching Function	-		-	-			Yes - Yes -	-	-	-	-	- T	es Y	es	Yes	Yes	Yes	Yes	Yes	-	-	-	- Yes	Yes	Yes Yes	- Yes	-	-	-		-	-	-	-		-	-	-	-
USB Memory Network Settings	-	-	-	-	-	-		-	-	-	-	- v	es Y	es	Yes	Yes	-	-	-	-	-	-		-	Yes	- 105	Yes	Yes	-		-	-	-	-			-	-	-
Memory Viewer	-	-	-	-	-		Yes -	-	-	-	-				Yes	Yes	-	-	-	-	-	-		-	res		Yes	Yes	Yes	Yes Yes	Yes	Yes	-	-		-	-	-	-
Input Search	Yes	Yes	Yes	Yes	Yes		Yes Yes	Yes	Yes	Yes	Yes 1				Yes	Yes	Yes Yes	Yes	Yes	Yes Yes		Tes	Yes		Yes		Yes \	es Y	es Ye	s Ye	s Yes	Yes	Yes						
Digital Zoom	ies -	Tes	Yes	Yes			Yes Yes		Yes						Yes	Yes	Yes	Yes		Yes		Yes	Yes Yes	Yes	Yes	Yes -	Yes	Yes	Yes	Yes -	res	res				s Ye			Yes
S Daisy-Chain Connection	-	-	Yes	Yes			Yes Yes		Yes						Yes	Yes	-	-	-	-	-	-		-	Yes	Yes Yes		Tes	-			-			es Ye				-
Frame Creation	Yes	Yes	10.5	103	103	103	103 103	103	103	103	-				Yes	Yes	Yes	-					- Yes	-	105	103 103	Yes	Yes	Yes	Yes -	_		103	-	-	.5 10	5 105	Yes	Yes
IR In/Out (Infrared signal) Connection	-	-	Yes	Yes	Yes	Yes	Yes Yes	Yes	Yes	Yes					Yes	Yes		Yes	Yes	Yes	Yes	Yes	Yes Yes		Yes	Yes Yes		<sup>6</sup> Yes <sup>*6</sup>	103	103	-		Yes	es Y	es Ye	s Ye	s Yes		103
Failover/Failback*5	-	-	Yes	Yes			Yes Yes		Yes						Yes	Yes	-	-	-	-	-	-		-	Yes	Yes Yes		Yes			-	-				s Ye			-
Power on Screen Delay	Yes	Yes	Yes	Yes			Yes Yes		Yes						Yes	Yes	Yes Yes	Yes	Yes	Yes Yes		-	Yes	Yes -	-	-				s Ye			Yes						
Picture in Picture	-	-	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-		-	-	Yes	Yes -	-	-	-	-			-	-	-
Brightness Sensor	Yes	Yes	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-			-	-	Yes	Yes -	-	-	-	-			-	Yes	Yes
No Activity Power OFF	Yes	Yes	Yes	Yes	Yes		Yes Yes	Yes	Yes	Yes			_	es	Yes	Yes	Yes	Yes	_	Yes	_	Yes	Yes Yes	Yes	Yes	Yes Yes		-	Yes	Yes -	- 1	-	Yes )	es Y	es Ye	s Ye	s Yes		Yes
No Signal Power OFF	Yes	Yes	Yes	Yes	Yes		Yes Yes		Yes		Yes				Yes	Yes		Yes		Yes		Yes	Yes Yes	Yes	Yes	Yes Yes		Yes	Yes	Yes Yes	Yes	Yes	Yes 1	(es Y	es Ye	s Ye	s Yes	Yes	Yes
Input/Button Lock	Yes	Yes	Yes	Yes			Yes Yes		Yes						Yes	Yes		Yes		Yes		Yes	Yes Yes	Yes	Yes	Yes Yes		Yes	Yes	Yes Yes		Yes	Yes		es Ye	s Ye	s Yes	Yes	Yes
Early Warning Software*7	Yes	Yes	Yes	Yes			Yes Yes								Yes			Yes		Yes			Yes Yes		Yes	Yes Yes				Yes -	-	Yes				s Ye	s Yes		Yes
Multi Monitoring & Control Software	-	-	Yes	Yes			Yes Yes		Yes						Yes			Yes		Yes			Yes Yes		Yes	Yes Yes				Yes -	-	Yes				s Ye			Yes
Video Wall Manager/Auto Display Adjustment Upgrade Kit	-	-	Yes*8				es*8 Yes*8							es*8 )		Yes*8				Yes*9	-	-		Yes*9	Yes*8			-	-		-			es*8 Ye			*8 Yes*8	-	-
5 Control Management Software	-	-	Yes	Yes			Yes -	-	-	-	-				Yes	Yes	-	-	-	-	-	-		-	-		-	-	-		-	-		res Y	es -	-	-	-	-
Super High Quality Up-Scaling	Yes	Yes	-	-	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-		-	-	-		-	-	-	-			-	-	-

\*1: TH-55/49/42LF80 only. \*2: TH-65SF2E, SF2W models only. \*3: TH-98/84LQ70 only.
\*4: Limitations exist for USB input. For details, please see the User's manual.
\*5: Switching time depends on models and setting. \*6: Failover only.
\*7: Suffix of the part number may differ depending on the license type.
\*8: Download the latest Video Wall Manager from PASS in advance. [https://panasonic.net/cns/prodisplays/pass/]
\*9: Supports Video Wall Manager only.



Weights and dimensions shown are approximate. Specifications and appearance are subject to change without notice. Product availability differs depending on region and country. This product may be subject to export control regulations. Windows, Windows Vista and PowerPoint are trademarks of Microsoft Corporation in the United States and other countries. Android is a registered trademark or trademark of Google Inc. Macintosh, Mac, Mac OS X, iPad, iPhone, iPod touch and iTunes are trademarks of Apple Inc., registered in the U.S. and other countries. The PJLink trademark is an application trademark in Japan, the United States, and other countries and regions or registered trademarks. HDMI, the HDMI logo, and High-Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing LLC in the United States and other countries. Crestron Connected™ is a trademark of Crestron Electronics, Inc. Miracast are trademarks or registered trademarks of Wi-Fi Alliance. HDBaseT is a trademark of the HDBaseT Alliance. "LinkRay", "LinkRay" icon and OpenPort PLATFORM are trademarks of Panasonic Corporation. All other trademarks are the property of their respective trademark owners. Images on screen are simulated. © 2017 Panasonic Corporation. All rights reserved.











For all the latest information on Panasonic projectors and professional displays download our app to your iOS/Android device.

For the latest information about Panasonic Professional Displays, please visit:

Professional Display European Website – business.panasonic.co.uk/ visual-system/products-and-accessories/professional-displays YouTube – www.youtube.com/user/PanasonicBusiness Facebok – www.facebook.com/PanasonicVisualSolutionsEU/

All information included here is valid as of February 2018